

CXDI-1 System

CXDI-50G *Service Manual*

Manual Control No.	: BY8-2257-0E2
Name of Product	: CXDI-50G
Distribution Control No.	
Issued on	

Service Manual Introduction

This service manual belongs to a series of after-service guides Canon Inc. publishes as part of its comprehensive product quality guarantee program.

This service manual consists of seven chapters; General Information, Installation Guide, Feature Information, Repair Guide, Parts Catalog, Troubleshooting and Service Manual Report.

If the product undergoes a large modification, a new service manual of revised edition will be sent to you. In other cases, service manual report will be sent to you updates the manual.

Note 1:

This service manual is published by Canon Inc. in accordance with Article 6 (Furnishing the Referent Materials) of the Service Assignment Contract it has concluded with your company.

Note 2:

This service manual property of Canon Inc. and the company may seek to have it returned, depending on circumstances. You are expected to keep it until then.

Note 3:

You inquiries, suggestions etc. about the contents of this service manual should be addressed to:

Medical Products Technical Service Dept.

Canon Inc. Utsunomiya Optical Products Operations

20-2 Kiyohara-Kogyodanchi, Utsunomiya-shi, Tochigi-ken 321-3292

JAPAN

Caution Regarding Service

This product was precisely assembled under strict manufacturing process control. There are several hazardous locations inside of this product. Careless work while the cover is removed can result in pinching fingers or cause electrical shock. Please perform the work with the following important points in mind:

1. Setup, Repair and Maintenance

In order to ensure safety, the best performance, setup, repair and maintenance work can only be performed by the technicians received the service training specified by Canon Inc. If there are order required certificates or restrictions specified by the law or ordinances, those regulations of the country must be observed.

2. Removing the external cover

When removing the cover during maintenance, repair, etc., perform the work after switching the power off. Never touch the device with wet hands, as there is a risk of electric shock.

3. Fuse

When replacing the fuse, first, resolve the reason of failure and then replace the fuse with the specified type. Never use a fuse other than the specified type.

4. Connecting the grounding wire

The provided ground wire must be connected to the ground terminal indoors. make sure that the device is properly grounded.

5. Alternation prohibition

Never modify the medical device in any way.

6. Waste control

The service provider is responsible for the disposal of used service parts, packing material, etc. resulting from the setup, repair or maintenance of the medical device. However, the customer is responsible for the disposal of the medical device. Disposal activities must follow the regulations (=specially controlled industrial waste) of the country where the device is used.

Caution regarding the setup

According to the “IEC60601-1-1:2000”, devices installed in the patient environment are restricted to “electric medical devices conforming to IEC60601-1”.



The Control PC, operation unit, and the magnetic card reader, etc. options that are parts of the CXDI-C3S are classified under the data processing device standard (IEC60950), therefore these items should not be installed in the patient environment. Otherwise the Control PC is only classified in CXDI-C3S.

The patient environment described below is an example cited from the “IEC60601-1-1:2000” – the measurements are only guidelines. However, the “IEC60601-1-1:2000” example must be treated as the standard.

Therefore, the CXDI-C3S must be installed in a location further than the measurements below (outside of the patient environment).

***Areas where the patient moves (not only during imaging but when entering and leaving the room, etc.) are also considered as part of the patient environment, therefore the installation location should be determined upon consultation with the user regarding areas outside of the patient environment.**

Example of patient environment



IEC 2513/2000

Note: The measurements are only guidelines.


CXDI-50G

1. General

Content

1	CXDI-1 System Block Diagram.....	1
2	System Diagram	2
3	CXDI Image Processing	3
4	Specifications.....	4

1 CXDI-1 System Block Diagram
(CXDI-50G)




Symbol	Description	Remarks
CA1	AC Cable	3m
CA2	50Sensor Cable	3m/7m
CA3	X-Ray I/F Cable	20m
CA4	LAN Cable (Category 5)	
CA5	LAN Cable (Category 5)	10m
CA6	Serial Cable (Touch Panel)	2m
CA7	VGA Cable	1.5m
CA8	AC Cable	3m

1. General

2 System Diagram


2.1 Standalone System

Standalone System Block Diagram



2.2 Total System


Total System Block Diagram (Example)



1. General

3 CXDI Image Processing

3.1 Process Flow



3.2 Image Types

(1) BORN IMAGE

The image obtained with LANMIT before any correction is made.

Outside distribution of these images is prohibited, including dtstore images.

(2) RAW IMAGE

Born image after offset processing, gain correction.

This is the image with LANMIT specific characteristics corrected.

(3) ORIGINAL IMAGE

Raw image after preprocessing.

(4) QA IMAGE

Original image after gradation processing, sharpening, and other processing.

The CXDI performs image processing up to this point.

(5) DIAG. IMAGE

QA image after further image processing necessary for diagnosis.

Image processed by the user for diagnostic purposes.

(6) PROCESSED IMAGE

Diagnosis image after post-processing.

Image modified by the user or the default processed image.

1. General

4 Specifications

The CXDI-50G (Imaging Unit/Power Box) is the Digital Cassette that has the mobility and can be used on the optional angles.

(1) Imaging Unit

This unit consists of the internal sensor, 50Di Board, 50AD Board, 50LED Board and its outer cover. The sensor unit converts the X-ray image to the electrical signal (O/E Conversion) and after performs the A/D conversion, transfer its signal through the Power Box with Ethernet cable to the Control PC.

Item	Content	Remarks
Object	General Shooting Cassette	(Mobile/Desktop PC)
Effective filming range	353 x 430mm	
Number of Pixels	2214 x 2700	
Effective Number of Pixels	2208 x 2688	
Pixel pitch	160μm x 160μm	
Fluorescent substance	GOS Fluorescent screen	
Output gradations	12bit (4,096 gradations) A/D 14bit	
Transfer method	Ethernet: Imaging Unit to Control PC (Through the Power Box)	
Imaging cycle	15 sec. (standard)	
Dimension	491 (W) x 477 (D) x 23 (H) mm	Including handle portion 427 mm (excluding handle portion)
Imaging Unit coloring	Cool white	
Imaging Unit mass (except Grid)	4.8Kg	Except the cable
	5.7Kg	With 7m cable
	5.2Kg	With 3m cable
Distance	Space between surface where patient gets in contact (CFRP) and sensor surface (glass) is within 5.1±0.5mm.	
Heat emission	15kcal/h	
Mechanical strength*1	Cassette with resisting the strength (Original specification)	Load uniformly: 150Kg Load partly: 100Kg/φ40mm
Control PC	CXDI-C3S General PC in market	
Power Control (ON/OFF)	None (Power Box: Operation with Remote switch manually)	
Grid attach/remove detector	Yes	
Cable for Imaging Unit	3/7m 2types	Distinguish with Product order.
Count of connected sensor	One Imaging unit can be connected with one Control PC	
Scattered radiation backward block sheet	Mo sheet (0.3 mm thick)	
Environment-conscious unleaded type		
Photo timer	Cannot be built in	

*1: The Imaging unit is put on the plain surface with the Sensor side (Detector) is up.

1. General

Item	Content	Remarks			
Imaging restriction (Imaging Prohibition)	When the internal temperature of Imaging Unit is above 49 degree Celsius, its state is changed to sleep mode. And the Imaging prohibition will be continued when the internal temperature is below 48 degree Celsius.				
User interface	Single type LED Off: Imaging unit power is off On in orange: Imaging unit power is on (unable to perform imaging) Blinking in green: Preparing imaging/error status On in green: Imaging preparation is complete	INDICATION	BUSY	SENSOR	POWER
		Color	Orange	Green	Blue
		Imaging unit is off	Off	Off	Off
		Imaging unit is on	--	Off	On
		Preparing imaging	--	Blinking ^{*1}	On
		Imaging preparation complete	--	Off	On
		Error status	--	Blinking ^{*2}	On
		Communicating	Blinking ^{*3}	--	On
		Initialization (when startup)	--	Blinking ^{*4}	On
		Network not set (when startup)	--	Blinking ^{*5}	On
		^{*1} : Turns on and off for 0.5 seconds each ^{*2} : Turns on and off twice for 0.5 seconds, then turns off for 0.5 seconds ^{*3} : Turns on and off randomly ^{*4} : Fades in for 1 second and fades out for 1 second ^{*5} : Fades in for 2 seconds, and then turns off			

1. General

(2) Power Box

This unit consists of 50XRAY Board, 50Power Supply and its outer cover.

The function; the signal transition between Imaging unit and Control PC, the interface to the X-ray generator equipment and power supply to the Imaging unit has been implemented.

Item	Content	Remarks
Communication interface standard	IEEE* 802.3u (100BASE-TX)	Connector type: RJ45
Communication method	Asynchronous serial communication method	Data length: 10bit Data rate: 15.625 kHz
Power supply	AC 100-120V \pm 10% 50/60Hz 1.5A AC 200-240V \pm 10% 50/60Hz 0.8A	Reference CXDI-50G Power supply Rated Voltage: AC 100-120V (AC 85-132V) AC 200-240V (AC170-264V)
Mass	4.2 Kg	
Dimension	358(W) x 200(D) x 65(H)* mm	Except bottom rubber parts (With bottom rubber parts: 75mm)

(3) Environment rated parameters

Item	Content	Remarks
Operating temperature	+5 to +35°C	Must be without dewing
Operating humidity	30 to 75% RH	
Keeping or Transporting	Temperature: -30 to +50°C Humidity: 10 to 60% RH Atmospheric pressure: 700 to 1060 hPa	

* IEEE: Institute of Electrical and Electronic Engineers

CXDI-50G

2. Installation Manual

Content

1	Caution during the installation	1
2	Product Configuration	2
3	Packing Diagram	5
4	Installation Procedures	7
4.1	Lists of Tool Needed for Installation	7
4.2	System Installation Procedures	8
5	Installation	10
5.1	Connection to each unit.....	10
5.2	Starting up and shutting down the System.....	16
5.3	X-ray Controller Interface.....	17
5.4	Network Settings 1.....	23
5.5	Setting the Fixed ROI Areas	26
5.6	Settings.....	29
5.7	Image Quality.....	85
5.8	Post-installation checks.....	87
6	Dimension.....	89

1 Caution during the installation

Please pay attention to the followings when installing the system.

- (1) If the equipment is hoisted, lowered or transport, it must be supported at both sides by a minimum of two people so there is no danger of it falling.
- (2) If a forklift, etc. is used to transport the equipment, make sure there is nothing that could impede the forklift on its route to the final destination.
- (3) When installing the equipment, be sure the site meets the following criteria:
 - 1) There must be no dripping water in the area.
 - 2) The environment must be free of harmful elements such as humid or acidic air, air with a saline or sulfur content, where there is poor ventilation or where air pressure or temperature is unusual.
 - 3) The equipment must not be placed at an angle or subjected to vibration or shock (this includes during transportation).
 - 4) The equipment must not be kept where chemical products are stored or where gasses are generated.
 - 5) The site's power supply must be of the correct voltage and frequency for the equipment.
 - 6) The site must be connected to a fully earthed cable with sufficient ground resistance to meet standard values.
- (4) After installation, be sure to dispose of waste product packaging with care and with full respect for the environment.



2. Installation Manual

2 Product Configuration







2.1 Product Configuration List

No.	Item Name	Qty	Remarks
1	CXDI-50G Imaging Unit	1	With Sensor cable (3/7m)
2	Power Box	1	100 - 120/230V
3	X-ray I/F cable	1	20m
4	Remote switch	1	20m
5	Cable connector clump	1	For preventing the power cable connector from coming off
6	Screw (M3 x 4 mm)	2	For fixing the cable connector clump
7	Cable clump	1	For fixing the sensor cable
8	Screw (M4 x 6 mm)	1	For fixing the cable clump
9	Sensor Information File (FD)	1	
10	Power supply cable (with AC plug)	1	3m (100/120/230V)
11	Attached documents for medical	-	(100V)
12	Certifications (warranty registration, inspection compliance, operation manual)	-	(100V)
13	Inspection compliance, operation manual	-	(120/230V)
14	Packaging	-	



2.2 Configuration

No.	1	No.	2
Name	CXDI-50G Imaging Unit	Name	Power Box
Qty	1	Qty	1
Remarks	3/7m	Remarks	I/F and Power supply (3/7m)
			

2. Installation Manual

No.	3	No.	4
Name	X-ray I/F cable	Name	Remote switch
Qty	1	Qty	1
Remarks	Connection with X-ray generator	Remarks	Power Box power source ON/OFF
			
No.	5	No.	6
Name	Cable connector clump	Name	Screw (M3 x 4 mm)
Qty	1	Qty	2
Remarks	For fixing the Power cable	Remarks	For fixing the cable clump
			
No.	7	No.	8
Name	Cable clump	Name	Screw (M4 x 6 mm)
Qty	1	Qty	1
Remarks	For fixing the sensor cable	Remarks	For fixing the cable clump
			


2. Installation Manual

No.	9	No.	10
Name	Sensor Information file FD	Name	Power supply cable
Qty	1	Qty	1
Remarks		Remarks	For Power Box (100/120/230V each type)
			


3 Packing Diagram

3.1 X-ray Digital Camera System (CXDI-50G)

(1) CXDI-50G assemble package




(2) CXDI-50G Imaging Unit package




2. Installation Manual

(3) CXDI-50G Power Box assemble package



(4) Grid (optional)



2. Installation Manual

4 Installation Procedures

4.1 Lists of Tool Needed for Installation

Tool needed for new installation.

No.	Tool Name	Unit	Remarks
1.	General Tools	1 set	
2.	Note PC	1	PC/AT compatible (OS: Microsoft Windows XP Professional recommend)
3.	LAN Card	1	For Note PC (as required)
4.	Mouse	1	PS/2 type
5.	Keyboard	1	PS/2 type
6.	HUB	1	Connection between Control PC and Note PC
7.	10/100BASE-TX cable	2	Straight type (Control PC to Note PC)
8.	CXDI Software version compatibility table	-	
9.	Mirror, oil-based marker and paper etc.	1	For adjusting the alignment with the X-ray tube.

2. Installation Manual

4.2 System Installation Procedures

No.	Step	Conditions and Checkpoints	Reference Section
1	Unpacking and checking the product's constituent parts	-There must be no missing parts, damage, dents, etc. -There must no color changes in the shock sensor.	
2	Connect the Imaging Unit and the Power Box	-Handle the instrument carefully, as it may be damaged if something is hit against it, dropped or receives the strong jolt. -The cable must be routed in such a way that no unreasonable loads are brought to bear upon them.	
3	Connect the Power Box and the Control PC	-The cable must be routed in such a way that no unreasonable loads are brought to bear upon them.	
4	Connect the Power Box and the X-ray generators	-The manufacturer of the X-ray generators must be asked to handle the connections with the generators.	
5	Check date and time	- Date and time must be changed according to the area where the instrument is installed.	"(1) Checking and Setting the Date and Time" in section 5.6.
6	Check the software program's version	-The compatibility of the sensor unit and the Control PC must be checked on the compatibility list, and the software program must be installed or upgrade as required.	"(2) Checking the Firmware Version" in section 5.6.
7	Identifying the Imaging Unit (input the sensor serial numbers)		"(6) Identifying the Sensor Units" in section 5.6.
8	Enter control PC serial number.		"(7) Entering Control PC Serial Number" in section 5.6.
(9)	Adjusting the timing with X-ray generator	-No required usually.	
10	Calibration	-No error must be displayed.	Operation Manual
11	Setting the Fixed ROI Areas	If necessary, set the ROI area.	
12	Set exposure parameter table	-Set it in consultation with the technician.	"(8) Table Setup Setting" in section 5.6.
13	Set annotation	-Set it in consultation with the technician.	"(9) Performing the Annotation Setting" in section 5.6.
14	Connect the network and set the output destination		"(10) Network Connections" in section 5.6.
15	Startup settings		"(5) Set Up Startup Menu" in section 5.6.
16	Exposure testing	-The data must be sent to the printer and storage and the image quality must be checked.	Section 5.7 Image Quality.
17	Check the linearity of the transferred image density.		"(11) Linearity Check Image Density" in section 5.6.
18	Operation unit Gamma correction		"(12) Operation Unit Gamma Correction" in section 5.6.
19	Body parts settings	-The engineer in charge must be consulted prior to perform these settings.	Operation Manual
20	Check and set the system settings.	-The engineer in charge must be consulted prior to perform these settings.	Each section in section 5.6 Settings.
21	Total adjustments and delete the unnecessary data.	-Conform according to the check sheet. -Delete the unnecessary data.	Section 5.8 Post-installation check.
22	Cleaning		

2. Installation Manual


23	Explain the operation to the user		Operation Manual
24	Final parameter adjustment	-The engineer in charge must be consulted prior narrowing down the adjustments to the final values.	Operation Manual
25	Inserting the backup floppy disk.	-It must be confirmed at re-start that backup files have been made. -No necessary for the system installed in vehicles.	“(15) Backing up Setting Data to FD” in section 5.6.
26	Back up valuable data		“(14) Backing Up when Installing” in section 5.6.

2. Installation Manual

5 Installation

5.1 Connection to each unit

5.1.1 Connection diagram




2. Installation Manual


5.1.2 Connecting to the Power Box

(1) Removing the cover

Remove the 5 screws from the back of the power box and the 2 screws on each side at the bottom of the power box.



(2) Check the jumper pin settings on the PCB-50XRAY board in the power box. The power supplies for 7m and 3m are not compatible due to having different output voltages. This short pin is for determining the power, not for changing the voltage.



With changing the jumper pin settings, the signal sent to PLD (IC1) of the PCB-50XRAY board has either state High or Low. By using this state, the PBIF50XRAY PLD code which written in the PLD can distinguish whether the power supply is for 3m or 7m.


When the echo signal for checking the cable connection and determining if the power box is 3m or 7m is sent from PCB-50Di board on the Imaging unit, the PBIF50XRAY PLD code echoes back with a noninverted if the signal is for 3m and an inverted signal if the signal is for 7m.

The Imaging unit determines the cable length based on the dip switch setting (SW1-7: OFF) on the PCB-50Di board. If cable connector P4 #1-#2 is open, cable length is 7m. If #1-#2 is connected, cable length is 3m. Based on the signal echoed back from the PCB-50XRAY board and the dip switch setting, the imaging unit checks if the communication system is working properly, while also checking if the power box information (3m/7m) and cable length information are consistent.


2. Installation Manual

(3) Cable connections

- 1) Loosen the lock nut for each cable and connect the cables to the power box. Then fix the cables by tightening the lock nuts.





- 2) Attach the cable clamp to the sensor cable, and then fix it to the power box using the screw (M4 x 6 mm).




2. Installation Manual

- 3) Connecting each cable connector.





- 4) After completing the connections, attach the power box cover.
5) Connect the LAN cable to the back of the power box.




2. Installation Manual

- 6) Connect the power cable to the back of the power box.
After connecting the power cable, fix the cable connector clamp using 2 screws (M3 x 4 mm).



2. Installation Manual

5.1.3 Connection diagram for Control PC rear panel



5.2 Starting up and shutting down the System

Perform the following sequences when starting up and shutting down the system.

5.2.1 Sequence for Starting up the System

Perform the following sequence when turning the system power on.

If you do not perform the correct sequence, the imaging unit cannot be recognized, resulting in an error. (This is because the system communicates with the imaging unit when turning the system on.)

The power box cannot be turned on in conjunction with turning on the control PC.

Since the power box is equipped with a remote switch that turns on/off the secondary output, you can install the switch on your side to turn it on/off.

- 1) Turn on the main power of the 50G power box.
- 2) Turn on the remote switch of the 50G power box.
- 3) Turn on the control PC.

Note:

Ccrstart.bat should be registered in Windows Startup.

5.2.2 Sequence for Turning the Power off (Shutdown)

- 1) From OPU, select SYSTEM → [SHUTDOWN] or [SHUTDOWN after transfer]

The control PC automatically turns off.


- 2) Turn off the remote switch of the power box.
- 3) Turn off the main power of the power box.

Note:

Turn off the main power of the power box and OPU power when not using the system for a long period.


5.3 X-ray Controller Interface

5.3.1 Interface Signal Description




2. Installation Manual

- When normal imaging



- When timeout due to RX_REQ not negating




2. Installation Manual

5.3.2 Signal names and functions in the connection with the X-ray generator

<X-ray Sync Signal>

Signal name	Functions
RX_REQ	<p>X-ray exposure signal Indicates that an X-ray exposure is ordered at the X-ray generator side. This signal needs to be retained at least for T_{PREP} period. X-ray release signal (RX_COM) is not output if the T_{PREP} is less than the necessary period. It takes about 1 second in the worst case scenario before the operation can be resumed when RX_REQ is negated in this period. Time required to assert RX_COM after receiving the RX_REQ from the X-ray generator T_{PREP}..... min. 300 ms</p> <p>Since a captured image is read from the sensor when RX_REQ is negated (or RX_COM is time out) as a trigger, reading action is delayed if RX_COM does not negate and time out is used as the trigger, resulting in delay of image display timing. We recommend using a configuration in which RX_REQ is negated.</p> <p>Time required from X-ray exposure completion to negating RX_REQ $T_{RX_REQ_NEG}$ min.0 max.100ms * Image display timing is delayed if this is not fulfilled.</p>
RX_COM	<p>X-ray release signal Checks whether or not imaging is ready at the CXDI side after receiving X-ray exposure signal (RX_REQ) from the X-ray generator. This signal is output to the X-ray generator side when imaging is ready.</p> <p>Time required from asserting RX_COM to exposing X-ray T_{PRE_DELAY} min.0 max.100ms * Available imaging time is reduced if this is not fulfilled.</p> <p>Time required to stop X-ray exposure after RX_COM halts T_{POST_DELAY} min.0 max.100ms * Shading could occur on images if this is not fulfilled.</p>

2. Installation Manual



The connection with CXDI-50G and X-ray generator equipment

Connecting condition

- (1) The X-ray emission signal line impedance is below 100Ω.
- (2) The max voltage at the point of X-ray release signal line is AC250V max, DC30V max and its current is from 10mA to 2A. However only 2nd Power source side is available for connecting.

2. Installation Manual

5.3.3 Rating and Characteristics for Relay and Photo coupler (on PCB-50XRAY Board)

(1) RL1 (Power Relay/Plug-in terminal type)

1) Rating (Operational coil)

Type	Rated voltage (V)	Rated current	Coil resistance (Ω)	Coil Inductance (ref. value) (H)		Pick-up voltage (V)	Dropout voltage (V)	Maximum voltage (V)	Power consumption (VA,W)
		(mA)		Armature OFF	Armature ON				
2-Pole type	DC12	43.6	275	1.15	2.29	below 70%	below 15%	170% (at 23)	Approx 0.53

2) Rating (Switch/Contact)

Type	Non-latching	
Pole	1 pole type	
Load	Resistive load	Inductive load (p.f = 0.4, L/R = 7ms)
Contact mechanism	Single	
Contact material	A g C d O	
Rated load	5A at 250VAC 5A at 30 VDC	2A at 250VAC 3A at 30 VDC
Carry current	5A	
Max. operating voltage	AC380V,DC125V	
Max. operating current	5A	
Max. switching capacity	AC1250VA DC150W	AC500VA DC90W

3) Characteristics

Item		Content
Pole		2 pole
Contact resistance		Below 50mΩ
Operate (set) time		Below 15ms
Release (reset) time		Below AC10ms, belowDC5ms
Operating frequency	Mechanical	18,000 operations/h
	Electrical	1,800 operations/h (under rated load)
Dielectric strength		Between Coil and Contact: AC5,000V 50/60Hz 1/min Between same polarity AC3,000V 50/60Hz 1/min
Vibration	Mechanical durability	10 to 55 Hz; 1.50mm (0.06) double amplitude
	Malfunction durability	
Service life	Mechanical	AC: 10,000,000 operations min. DC: 20,000,000 operations min. (at 18,000 operations/hour)
	Electrical	100,000 operations (under rated load, at 18,000 operations/hour)
Ambient temperature		-40 to 70°C (-40 to 158°F) (with no freeze and no dew)
Humidity		35% to 85% RH

2. Installation Manual

(2) PCI (Photo-coupler)

1) Maximum Ratings (Ta = 25°C)

CHARACTERISTIC		SYMBOL	RATING
LED	Forward Current	$I_F(\text{RMS})$	50 mA
	Forward Current	$\Delta I_F/^\circ\text{C}$	-0.7(Ta≥53°C)
	Pulse forward current ¹	I_{FP}	1 A
	Reverse Voltage	V_R	5 V
DETECTOR	Collector-Emitter Voltage	V_{CEO}	80 V
	Emitter-Collector Voltage	V_{ECO}	7 V
	Collector Current	I_C	50 mA
	Collector Power Dissipation (1 Circuit)	P_C	150 mW
Total Package Power Dissipation (1 Circuit)		P_T	200 mW
Isolation Voltage ²		BVs	2500 Vms

2) Maximum Ratings (Ta = 25°C)

CHARACTERISTIC		SYMBOL	TEST CONDITION	MIN.	TYP	MAX.	UNIT
LED	Forward Voltage	V_F	$I_F=10\text{ mA}$	1.0	1.15	1.3	V
	Reverse Current	I_R	$V_R=5\text{ V}$	-	-	10	μA
	Capacitance	C_i	$V=0, f=1\text{ MHz}$	-	30	-	pF
	Max. Forward current	V_{FM}	$I_{FM}=0.5\text{ A}$	-	3	4	V
DETECTOR	Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	$I_C=0.5\text{ mA}$	80	-	-	V
	Emitter-Collector Breakdown Voltage	$V_{(BR)ECO}$	$I_E=0.1\text{ mA}$	7	-	-	V
	Collector Dark Current	I_{CEO}	$V_{CE}=48\text{ V}$ Ambient Light Below (100lx)	-	0.01 (2)	0.1 (10)	μA
			$V_{CE}=48\text{ V}$, Ta=85 Ambient Light Below (100lx)	-	2 (4)	50 (50)	
SWITCH CHARACTERISTIC	Rise Time	t_r	$V_{CC}=10\text{ V}$ $I_C=2\text{ mA}$ $R_L=100\Omega$	-	2	-	μs
	Fall Time	t_f		-	3	-	
	Turn-On Time	t_{ON}		-	3	-	
	Turn-Off Time	t_{OFF}		-	3	-	
	Turn-On Time	t_{ON}	$V_{CC}=5\text{ V}$ $I_F=16\text{ mA}$ $R_L=1.9\text{ k}\Omega$	-	2	-	μs
	Storage Time	t_S		-	25	-	
	Turn-Off Time	t_{OFF}		-	40	-	

Note: Because of the construction, leak current might be increased by ambient light. Please use photo-coupler with less ambient light

¹ pulse amplitude 100μs, frequency 100Hz

² AC, 1min R.H.≤60 LED side pins shorted together and DETECTOR side pins shorted together

5.4 Network Settings 1

1. Objective

The CXDI-50G imaging part communicates with the control PC by using Ethernet [IEEE802.3u (100Base-TX)] to transfer X-ray images.

The control PC performs DICOM transfer in order to use Ethernet to transfer the obtained images to the printer and storage device.

This section describes how to set up the TCP/IP that is necessary for the network connection.

Set up the following three items:

- 1) TCP/IP setting for the control PC network card
- 2) Network setting for Screwcap.ini
- 3) Network setting stored in the CXDI-50G sensor

2. Preparation

- Keyboard
- Mouse

Connect the keyboard and mouse to the back of the control PC.

Check if the system is connected, and then turn the system on.

3. Setup method

3.1 TCP/IP setting for the control PC network card

Perform the set up by referring to “C3S Service Manual” -> the chapter “System Manual” -> “Network Setup”.

Default values

IP Address:192.168.100.10

SubnetMask:255.255.255.0

2. Installation Manual

3.2 Network setting for Screwcap.ini

The CXDI software communicates with the imaging part through screwcap.dll by using the communication protocol for sending and receiving commands and responses.


In conjunction with the communication, Screwcap.ini retains the information of the connected CXDI-50G and control PC such as network addresses.

It is necessary to edit Screwcap.ini to communicate with the imaging part.

Since the Screwcap.ini factory setting is the following default setting (see the figure below), it is not necessary to edit the setting unless you changed the network protocol TCP/IP setting for the LAN card that communicates with the CXDI-50G imaging part in the previous item, “3.1 TCP/IP setting for the control PC network card”.

Screwcap.ini is located in the following directory:

D:\ccr\screwcap.ini



*¹ CXDI-50G's IP address: This address must be the same as the IP address stored in the next item, “3.3 Network setting stored in the CXDI-50G sensor”.

2. Installation Manual

3.3 Network setting stored in the CXDI-50G sensor

The factory default setting is shown in the table below.

This setting is not necessary unless you have changed the setting.

Item to be set	Factory default value
Sensor IP address	192.168.100.11
Subnet mask	255.255.255.0
Host IP address	192.168.100.10
Port number for command	12121
Port number for data	12122

If you change the setting, refer to “Tool Software Instruction Manual for CXDI-50G” → “Imaging Part IP Address Setting”.

2. Installation Manual

5.5 Setting the Fixed ROI Areas


1) Purpose

Set the fixed ROI area on the sensor to expose by the fixed ROI area because user can not get the proper image by the Auto ROI area.

2) Setting method

2-1) Investigate the actual size and position of the ROI that is required.

2-2) Designate the SIZE, POSITION, and NUMBER (max 3) on the sensor.



2-3) Convert the size and position of the ROIs in 2) to pixel values. The pixel size of the sensor is $160\mu\text{m}$. For multiple values, use X' , Y' , W' , H' , X'' , Y'' , W'' , and H'' for calculations.

$$X/160\mu\text{m}$$

Let this value equal A

$$Y/160\mu\text{m}$$

Let this value equal B

$$W/160\mu\text{m}$$

Let this value equal C

$$H/160\mu\text{m}$$

Let this value equal D

2-4) Open the "DENSITY ADJUSTMENT CONTROL" screen when the normal imaging screen is active.


**SYSTEM→SETUP MENU→SYSTEM SETTINGS→
ADJUSTMENT CONTROL**

DENSITY


2. Installation Manual

2-5) The “DENSITY ADJUSTMENT CONTROL” screen appears. Confirm that the sensor is set with a sensor switch button. Press the [Fixed ROI Area] key.

2-6) Press the [Area setting] key.



2-7) The fixed ROI 1 setting screen appears. Input values A to D from step 3) into the edit box, and press [ENABLE]. To set multiple fixed ROIs, input A' to D' and A'' to D'' into fixed ROI 2 settings and fixed ROI 3 settings respectively.



2. Installation Manual

- 2-8) The display returns to the “DENSITY ADJUSTMENT CONTROL” screen. Confirm that POSITION and SIZE fields not set in step 5) to step 7) are disabled (dimmed). If they are not dimmed, press the [Area setting] key, and press [DISABLE] in fixed ROI * settings.



Check to make sure the displays are dimmed.

- 2-9) After Confirming all settings, and press [EXIT].

- 2-10) The display returns to the system settings screen. Press [OK].

- 2-11) “Change settings?” appears. Press [OK]. Be careful, because if [CANCEL] is pressed, all changes made to the settings are deleted.

“Change settings?” appeared.

- 2-12) Return to the normal imaging screen, and turn off the power to the CXDI.

5.6 Settings

(1) Checking and Setting the Date and Time

1) Purpose

The date and time is set to Japan standard time at factory shipment.

Reset the date and time to your local value as necessary.

2) Procedure

2-1) When CXDI application start, open the ADMINISTRATOR SETUP MENU.

SYSTEM → SETUP MENU → ADMINISTRATOR SETUP

2-2) When the “ADMINISTRATOR SETUP MENU” appears, and presses the [DATE] button.

2-3) The dialog (Date / Time Properties) appears, and set the value properly each of the fields which the tab sheet (Date&Time and Time Zone sheet) has. And then press [OK].

2. Installation Manual

(2) Checking the Firmware Version

1) Purpose

- 1-1) Failing to use the proper versions of the firmware and PLD code with the CXDI application can result in an error, and system operation cannot be guaranteed. Therefore, the versions of the firmware must be checked to ensure that they are correct. (The combination of this firmware refers to CXDI Software Combination List.)

2) Notes

- 2-1) This check should always be performed at installation, and if necessary, the firmware versions should be upgraded.
- 2-2) This check cannot be performed with only the control PC. Connect the imaging units and other equipment, and start up in the normal imaging status.

3) Procedure


3-1) Checking the firmware alone

a. Start up the CXDI system.

b. Display the version information from the user mode.

SYSTEM > SETUP MENU > VERSION INFORMATION

c. Confirm the firmware version.



A. Hardware version

This is the version of the 50Di PCB. It changes by the setting of the dipswitch on the PCB.

B. Firmware initialization code version

This is the version of the initialization code written on the 50Di PCB. Initialization code will be downloaded and settings will be reset to the default (factory) settings by turning ON the power while pressing the initialization switch on the power box.

Display "1.1.0" on the screen indicates version 1.01.00.

C. Firmware normal code version


This is the version of the normal code installed on the 50Di PCB. Usually the system operates with this code. It must be updated as required.

Display "1.1.00" on the screen indicates version 1.01.00.

2. Installation Manual

3-2) Checking the firmware and PLD code

- (1) Connect the keyboard and mouse.
- (2) Start up the CXDI system.
- (3) Close the CXDI host software if it starts up.
- (4) Connect Telnet by referring to “CXDI-50G Telnet Connection” in the Tool Software Operation Manual for CXDI-50G.
- (5) Check the versions of the firmware and PLD code on the screen displayed after the login.



```
login: canon
Password: *****
CXDI-50G firmware Ver.1.01.00
build as Jul 2 2003 16:13:45
normal boot
HUB50 Ver.5010 product code:0701
pcb-50di>
```

The screenshot shows a Telnet session. The text is as follows:

- login: canon
- Password: *****
- CXDI-50G firmware Ver.1.01.00
- build as Jul 2 2003 16:13:45
- normal boot
- HUB50 Ver.5010 product code:0701
- pcb-50di>

Labels with arrows point to the following lines:

- Firmware version points to "CXDI-50G firmware Ver.1.01.00"
- Hardware version points to "HUB50 Ver.5010 product code:0701"
- PLD code version points to "pcb-50di>"

- (6) After you finish checking, close HyperTerminal.

2. Installation Manual

(3) Installing Firmware and PLD Code

1) Purpose

Write exposure code and PLD code into the Flash ROM of the 50Di PCB in the imaging unit.

2) Notes

Be sure to check that the CXDI is connected to the system.

3) Procedure

3-1) Installing the firmware

Write the firmware by referring to “Firm Write Tool Software (Firmwrite.exe)” in the Tool Software Operation Manual for CXDI-50G.

Where to write: IC1 (Flash ROM) on 50Di PCB

3-2) Installing PLD code

Write PLD code by referring to “PLD Write Tool Software (pldwrite.exe)” in the Tool Software Operation Manual for CXDI-50G.

Where to write: IC10 (Flash ROM) on 50Di PCG

2. Installation Manual

(4) Checking the Sensor Serial No.

1) Purpose

If the sensor serial number and the sensor serial number stored in the flash ROM of the 50Di PCB differ from the image data file name stored in the hard drive of the Control PC due to replacing the PCB or imaging unit, the connected sensor can not be detected after the CXDI application is launched. In that case an error message appears.

2) Notes

2-1) Check the sensor serial No. whenever:

- a. 50Di PCB is replaced.
- b. Sensor in the imaging unit is replaced.

2-2) This checking procedure must be performed with the Control PC, Imaging Unit and all the other equipments connected and started up.

3) Procedure

3-1) Check the sensor serial No. by referring to “Sensor serial number setting” in the Tool Software Operation Manual for CXDI-50G, and write the number as required.

2. Installation Manual

(5) Set Up Startup Menu

1) Purposes

- 1-1) Register the CXDI application software to the “Startup Group”.

The CXDI application software is scheduled to start automatically at the CXDI system starting

- 1-2) Change the window view size

Hide the other application screen view except the CXDI application software.

- 1-3) Delete the CXDI application software from the “Startup Group”.

The CXDX application software is not started at the CXDI system starting.

2) Notes

- 2-1) The CXDI application software is not registered in the “Startup Group” at the factory setting.

Therefore register the CXDI application software to the “Startup Group” after the system installation.

- 2-2) The window view size of the program registered in “Startup Group” has one own size with the each short-cut icon. Be sure to set the window view size of CXDI application software at the same time with the register to the “Startup Group”.

3) Register the CXDI application software to the “Startup Group” procedure.

- 3-1) Connect keyboard and mouse to the control PC.

- 3-2) Turns the all CXDI system power on after the all installation finished. And after that Windows XP starts.

- 3-3) Open the “Taskbar and Start Menu” from the Start Menu.

Start⇒Settings⇒Taskbar and Start Menu

- 3-4) “Taskbar and Start Menu Properties” appears. Click “Start Menu” tab, and then click Taskbar and Start Menu Properties⇒Start Menu⇒Classic Start⇒Menu Customize

- 3-5) Click Add, and Create Shortcut appears. Click Browse.

- 3-6) Browse appears. Find a file named “ccrstart.bat” in drive [D:\ccr] and click OK.

- 3-7) D:\ccr\ccrstart.bat appears in the Command line. Click Next.

- 3-8) Select Program Folder appears. Select Startup folder and click [Next].

- 3-9) Select a name for the shortcut appears. Type ccrstart.bat. Click [Finish].

- 3-10) Close the Taskbar [Start], and login again to Windows XP.

Start⇒Shut Down⇒Log off cxdi.

- 3-11) After login the computer, make sure that the CXDI application starts up.

2. Installation Manual

- 4) Change the window view size
 - 4-1) After the CXDI application software start, press [Alt] + [Tab] key to show the “Debug mode” prompt screen.
 - 4-2) After the command prompt screen appears, click the icon (called System icon) where is in right-top of its window.
 - 4-3) System icon menu appears. Select Properties from the menu. [Fig 1]



[Fig 1]

- 4-4) Click the “Font” tab from the “ccrstart.bat” properties and change its size to “6 x 13”.
- 4-5) Click the “Layout” tab and change the “Height” of the “Screen Buffer Size” to 5000. Click [OK].
- 4-6) The “Apply Properties to Shortcut” appears and check the item of the “Modify shortcut which started this window”. Click [OK].
- 5) Delete CXDI application software from the “Startup Menu Group”.
 - 5-1) Connect the keyboard and the mouse to the control PC.
 - 5-2) Turns the CXDI system power on, Windows XP start.
 - 5-3) After the CXDI application software start, press [Alt] + [Tab] key to show the “Debug mode” prompt screen.
 - 5-4) Select “8 – Exit” to close the CXDI application software on the “Welcome to CCR”.
 - 5-5) After the CXDI application software closed and Window XP Desktop appear, open the “Taskbar & Start Menu...” with “Start Menu” tab clicking.
Start>Settings>Taskbar and Start Menu

2. Installation Manual

- 5-6) “Taskbar and Start Menu Properties” appears. Click “Start Menu” tab, and then click Taskbar and Start Menu Properties⇒Start Menu⇒Classic Start⇒Menu Customize
- 5-7) The “Remove Shortcuts/Folders” dialog box appears after click the “Remove” button. And double-click the “Startup folder”
- 5-8) Remove the “ccrstart.bat” item from it.
- 5-9) After “Remove” button clicked, the confirmation of deleting file appears. If you are going to remove it, click “Yes” button.
- 5-10) After confirm that the “ccrstart.bat” item is removed from “Startup Group”, close all the application on the desktop and re-login to Windows XP.
- 5-11) Make sure that the CXDI application software will not start automatically after login to Windows XP. And then shutdown Windows XP, turn the CXDI system power off.
 - * When the CXDI application is deleted from the Start menu due to repair or other reasons, be sure to always perform the procedures outlined in “Adding CXDI application software onto the Start menu” and “Changing the window size” when the repair is complete.

2. Installation Manual

(6) Identifying the Sensor Units

1) Purpose

In order for the control PC to identify the sensor units connected, the sensor serial number of each sensor unit is input to the Control PC.

2) Notes

2-1) These operations must always be implemented at the installation stage and when any of the Imaging Units (sensor) or Control PC (hard disk) has been replaced or when the combination of equipment has been changed.

2-2) The sensor serial numbers must always be input. If the serial numbers of the sensor unit and Control PC do not match, "Sensor Unit: Detect Error (-5100)" will be displayed on starting up the system. These numbers are the same as what is input to the 50Di PCB. (Refer to "Checking the sensor serial numbers".)

3) Preparations (What to have ready)

Tool keyboard, tool mouse

4) Procedure

4-1) Start up the CXDI unit.

4-2) Once the normal sensor screen has appeared on the operation unit, use the keyboard to enter the debugging mode (Use [ALT] + [TAB].).

4-3) "Welcome to CCR" appears. Select "1 Set-Up..."

4-4) "Setting Mode (0:Normal, 1:Expert)[0=0x0]:" appears. Select "0:Normal."

4-5) "CCR SETUP MENU" appears. Select "7 Scan Sensor Setup."

4-6) The "Capture Device Configuration Table" appears. Input "1" to the underlined part in "Max Capture Devices" shown below.

4-7) Enter the serial number to "A/D Board Serial Number for SensorID#1".

Enter the serial number here.

@@@@@ Capture Device Configuration Table @@@@@

Max Capture Devices [1=0x1]:1

@@@@@ Capture Device Configuration No.0 (SensorID#1 OPU)@@@@@

-----A/D Board Serial Number 0-0 -> 50G: 0x10000004

A/D Board Serial Number for SensorID#1 [0x10000004=268435460]:**010000004** ←

Custom Type [0:NO CUSTOM 1:STAND 2:TABLE 3:UNIV 4:CASSETTE]
[0=0x0]:0

Field of View Rotation (0:No 1:Yes) [0=0x0]:0

EXI constant [0.000000]: 0.000000

---- Need to re-start program to validate this change.

4-8) When "CCR SETUP MENU" appears, press the [Esc] key to return to "Welcome to CCR."

4-9) Select the command "8 - Exit" from "Welcome to CCR" menu to exit the CXDI application.

4-10) After "Windows XP desktop" screen appears, start the CXDI application again.

(7) Entering Control PC Serial Number


1) Purpose

Set the product serial number (Control PC) to the "Device Serial Number" of the "DICOM header".

2. Installation Manual

2) Procedure

- 2-1) Start up the CXDI system.
- 2-2) After the exposure screen appears on the operation unit, use the keyboard to enter Debug mode. (Use [Alt] + [Tab].)
- 2-3) “Welcome to CCR” screen appears. Select the command “1. Set-Up...”
- 2-4) The “Setting Mode (0: Normal, 1: Expert) [0=0x0]:” is prompted. Select “0: Normal”
- 2-5) “CCR SETUP MENU” appears. Select the command ”1. System Setup”.
- 2-6) “CCR Serial Number [0=0x0] : ” appears. Enter the six-digit number indicated on the naming label of the control PC unit. Press [Enter] key until “CCR SETUP MENU” appears. [Fig 1]

The screenshot shows a Windows NT desktop with a window titled "DemoStart.bat". The command prompt displays the following text:

```
C:\¥v410-dicom>echo off
chgini Ver.1.0.0.0 Copyright (c) 2000 Canon Inc. All rights reserved.
Welcome to Canon CXDI.
Copyright (c) 1996-2000 Canon Inc. Medical Dept. All rights reserved.
4.10.07, Jul  5 2001, 21:29:03
argument "no" set!
24-172921[70]ERR:##### 2001/07/24 V4.10.07 STARTED (This is not ERR) #####

***** Welcome to CCR *****
1 Set-Up...          5 -
2 Display Set-Up     6 - Utilities...
3 Image Util...      7 - Debug...
4 -                  8 - Exit
Enter item: 1
Setting Mode (0:Normal, 1:Expert) [0 = 0x0] : 0

***** CCR SETUP MENU (Esc to go back) *****
1 System Setup       6 Log Setup
2 OPU Control Info Setup  7 Scan Sensor Setup
3 IP Setup           8 -
4 Image Attribute Setup  9 -
5 Transmit Setup     10 -
Enter item: 1
CCR Serial Number [1 = 0x1] : 200001
```

An arrow points from a white box labeled "Enter here" to the input field for the CCR Serial Number.

[Fig 1]

- 2-7) Press [Esc] key after “CCR SETUP MENU” appears to return to “Welcome to CCR” screen.
- 2-8) Select “8-Exit” to exit CXDI application software.
- 2-9) This returns you to the Windows NT desktop. Restart the CXDI application, and perform the procedure from steps 2) to 5). Check that the serial number for the “CCR Serial Number” item was entered correctly in step 6).

*** Restart the CXDI application. The screen displays the following message:**

Alert System Info Error (-6) A/D board info is updated. Click “OK”

2. Installation Manual

(8) Table Setup Settings

1) Purpose

Adjust the CXDI operation unit's TABLE SETUP to match the exposure conditions (X-ray tube voltage, X-ray tube current, msec or mAs value) of the X-ray generator.

2) Procedure

2-1) Start the CXDI system.

2-2) Open the TABLE SETUP Change window from the Normal Exposure window.

System ⇒ SETUP MENU ⇒ SYS. SETUP ⇒ TABLE SETUP

2-3) Select the tabs to be changed and change the X-ray tube voltage, X-ray tube current, and msec value data to match the exposure conditions of the X-ray generator.

* See the operation manual for the details of settings.

2-4) After finishing the changes, return to the Normal Exposure window and check that the TABLE SETUP has been changed.

2. Installation Manual

(9) Performing the Annotation Settings

1) Purpose

The settings for imprinting the annotation onto the film and the settings of the characters used for the annotation are performed.

2) Procedure

2-1) Once the normal radiographic screen has started, open the annotation setting screen.

SYSTEM → SETUP MENU → SYS. SETUP → ANNOTATION

2-2) The annotation setting screen now appears. Proceed with the settings that will make it possible to put the data desired by the user.


*** See the operation manual for the details of settings.**

2. Installation Manual

(10) Network Connections

Network settings

- 1) Purpose
These settings are for connecting the CXDI to the network.
 - 1-1) Set the CXDI's IP address, subnet mask and default gateway in Windows XP.
 - 1-2) Set the printer and storage output destinations and parameters on the user screen.
- 2) Checkpoints
 - 2-1) This item involves checking the details of the checks performed on network setting parameters among the pre-installation inspection details and setting these parameters.
 - * **Refer to “Appendix: Investigation Report” for the pre-installation investigation details.**
 - 2-2) Perform the settings of this item carefully since any errors made in these settings will make it impossible for connection to be made to the network or the images to be transmitted properly, etc.
- 3) Windows XP settings
 - 3-1) Connect the keyboard and mouse to the control PC.
 - 3-2) After turning on the Operation unit's power and then the Control PC's power, start Windows XP.
 - 3-3) The Windows XP desktop screen appears. Right-click the [My Network] icon, and select My Network Places from the menu.
 - 3-4) When [Network Connection] appears, double click on Local Area Connection (Intel^(R) PRO/100VE Network Connection).
 - 3-5) When Local Area Connection Properties appears, click on the General tab, select [Internet Protocol (TCP/IP)], and click Properties.
 - 3-6) Based on the pre-install of inspection details set the IP address, subnet mask and default gateway.



[Fig 1]

2. Installation Manual

- 3-7) Upon completion of the setting, restart the Windows XP.
- 3-8) Check the communication test in the sequence below to verify whether the CXDI is now part of the network. To check the connections at the TCP/IP level, use the “ping” command from the command prompt.

Start → Programs → Command Prompt

When the IP address of the connection destination is “173.17.7.123,” for instance, the following messages will be repeated.

- If the CXDI has been connected properly:
Pic:>ping 172.17.7.123 (input on the DOS screen)
Pinging 17217.7.123 With 32 bytes of data:
Reply from 172.17.7.123:bytes=32 time <10ms TTL=255
Reply from 172.17.7.123:bytes=32 time <10ms TTL=255
Reply from 172.17.7.123:bytes=32 time <10ms TTL=255
Reply from 172.17.7.123:bytes=32 time <10ms TTL=2550
- If the CXDI has not been connected properly:
Pic:> ping 172.17.7.123 (input on the DOS screen)
Pinging 17217.7.123 With 32 bytes of data:
Request time out
Request time out
Request time out
Request time out

2. Installation Manual

- 4) Set the printer and storage device which serves as the external output destinations.
In this case, one printer and one storage device are set.

4-1) Printer settings

- A. Open the output destination setting screen from the user menu.

System → SETUP MENU → DESTINATION → PRINTER

*** Up to four printers (2 of which can be used for output at the same time) can be set.**

- B. Press the “Printer1” button, and input the following items based on the pre-installation investigation details.

a. Printer host name (IP address) b. Port number c. Transmission destination title

The screenshot shows a 'PRINT SETTING' window with a title bar containing 'ON' and 'Check the change(s)'. The window is divided into four sections for PRINTER1, PRINTER2, PRINTER3, and PRINTER4. Each section has a 'SET' button. PRINTER1 is currently selected and shows the following values: HOST: 192.168.1.20, PORT No.: 5040, and AE TITLE: CXDI. Arrows labeled 'a', 'b', and 'c' point to the HOST, PORT No., and AE TITLE fields of PRINTER1 respectively. PRINTER2, PRINTER3, and PRINTER4 are in a default state with empty fields. At the bottom of the window are 'CANCEL' and 'EXIT' buttons.

[Fig 2]

- C. Press the “SET” button, and input the parameters of the printer to be connected based on the pre-installation inspection details. (Refer to another sheet for details of the parameters.)

*** A space delimiter must be input between each of the parameters.**

By pressing the “Override” button, you can select a printer from all the registered printers. In this case, basically you do not have to enter parameters. However, if “?” is displayed within the parameters, you may have to enter the required parameter at the user’s site.

2. Installation Manual

Parameter -A 310 -T NO -M CUBIC -m ? -S LUT=0?,2?(?:Site Dependent)

Printer name PRINTER1

Pixel pitch 0 um

Override ▼

W x H			
11x14 ▼	3388	4277	CURRENT ▼
NONE ▼			
NONE ▼			
NONE ▼			

CANCEL EXIT

Input parameters

[Fig 3]

2. Installation Manual

4-2) Storage settings

- A) Open the output destination setting dialog from the user menu.
System → SETUP MENU → DESTINATION → STORAGE
*** Up to four storage units (2 of which can be used for output at the same time) can be set.**
- B) Press the “Storage1” button, and input the following items based on the pre-installation investigation details.
a. Storage host name (IP address) b. Port number c. Transmission destination title

The dialog box is titled "STORAGE" and contains four sections for storage units, labeled "No.1" through "No.4". Each section has a header with the unit name and a "SET" button. Below each header are three input fields: "HOST", "PORT No.", and "AE TITLE".

- No.1:** HOST is "CXDI_STORAGE1", PORT No. is "5040", and AE TITLE is "CXDI_STORAGE1". Callouts 'a', 'b', and 'c' point to these fields respectively.
- No.2:** Empty fields.
- No.3:** Empty fields.
- No.4:** Empty fields.

At the bottom of the dialog are "CANCEL" and "EXIT" buttons.

[Fig 4]

- C. Press the “SET” button, and input the parameters.
(Normally, the parameters need not be set. They must be input only when the need arises.)
- * A space delimiter must be input between each of the parameters.**

The dialog box is titled "STORAGE1". It contains two input fields: "Parameter" and "Storage Name". The "Storage Name" field is pre-filled with "STORAGE1". At the bottom are "CANCEL" and "OK" buttons.

[Fig 5]

2. Installation Manual

- D. After setting the output destinations, follow the procedure below to check whether images can actually be transmitted. Return to the user menu, capture a sample image (one X-ray image), and transmit the image to the printer and storage. There are two errors that may result if the image cannot be transmitted:
- a. “DICOM Connect Error. Cannot connect to the target. Check network or port number setting. Retry?”
 - b. “DICOM Transfer Error. Error occurred during the association. Retry?”

Message (a) indicates that connection at the TCP/IP level is not possible and that the physical connections or the subnet mask and other settings must be checked again.

Message (b) indicates that communication at the TCP/IP level is problem-free but that DICOM level communication has failed. In this case, check again that AE_TITLE of CXDI has been sent properly to the transmission destination and that the IP address, port number and AE_TITLE of the transmission destination which are set with CXDI have been set properly.

- * **“AE_TITLE” of the transmission destination is case sensitive fields.**
(Permit upper-case letter or lower case letter, etc)

2. Installation Manual

Parameter List (Separate Document 1)

DICOM storage device

In the CXDI, DICOM data transfer is performed using the transfer software module “send_image”. The settings for these parameters are described below.

Parameter	Meaning	Description
-m maxPDU Maximum PDU value in byte units	<ul style="list-style-type: none"> * The CXDI automatically uses 131072 internally for operation. * Designating a specific value allows overwriting of the above value. 	<ul style="list-style-type: none"> * The DICOM standards do not allow values of 1301073 or higher to be set. * This is used when the operator who manages the connected storage device requests a size change. * In DICOM printing, note that the argument title changes to -u. (→ See the printing parameters.)
-t calledTitle Called App Entity Title	<ul style="list-style-type: none"> * The AE Title setting field is automatically applied to this setting. * Designating a specific value allows overwriting of the above value. 	<ul style="list-style-type: none"> * Note that the meaning is opposite of the DICOM printing argument -c. (→ See the printing parameters.) * This is used when the operator who manages the connected storage device requests a change in the installed identification information (version).
-c callingtitle calling App Entity Title	<ul style="list-style-type: none"> * The CXDI automatically uses CANON_CCR internally for the operation. * Designating a specific value allows overwriting of the above value. 	<ul style="list-style-type: none"> * Note that the meaning is opposite of the DICOM printing argument -c. (→ See the printing parameters.) * This is used when the operator who manages the connected storage device requests a change in the installed identification information (version).
-s SOPName (for reference) This parameter designates whether class be connected for performing association at the beginning of transfer.(CR/T/MR/NM/S C/US)	<ul style="list-style-type: none"> * This is not used in the CXDI. 	
-I A-RELEASE-RES is ignored.	<ul style="list-style-type: none"> * This parameter is used simply as “-I” 	<ul style="list-style-type: none"> * This is used when the error message “30012 Peer aborted Association (or never connected)” occurs even though the DICOM data transfer was successful. → This is used differently based on the connected storage devices.
-d FAC This parameter dumps a specific facility log. (DCM/DUL/SRV)	<ul style="list-style-type: none"> * This parameter is used simply as “-d” * This parameter is used to make the transfer software put the debugging character string on the console. 	<ul style="list-style-type: none"> * This parameter does not affect DICOM data transfer. * This parameter outputs the CXDI log based on Windows NT.

2. Installation Manual

-v This parameter dumps the transfer log.	* This parameter is used simply as “-v”. * DUL and SRV are dumped. * This parameter is used to make the transfer software put the debugging character string on the console.	* This parameter does not affect DICOM data transfer.
-jn This is the time to take timeout.	* Sets the time to take timeout in seconds.	* This parameter is to be changed when taking timeout.

Argument: Values necessary for executing a function, subroutine, procedure, or other operation is passed to them. Arguments are assigned to functions and subroutines when executed. For example, the argument in f (x) is x.

PDU: Protocol data unit

The types of PDU's include get-request, get-next-request, get-response, set-request, nd trap.

Note

For details about the “-v” parameter, see “Checking the Error Log”.

Note

The parameters “-v” and “-d” put the log on the console. Therefore, be sure to always erase these parameters before operation by the user.

2. Installation Manual

Parameter List (Separate Document 2)

DICOM printer

In the CXDI, DICOM printers are administered separately according to printer product.

The transfer software module is “print_stuff”. The settings for these parameters are described below.

Parameter	Meaning	Description
-C copies This parameter uses a number to designate the number of copies.(1/2/...)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Film Session (2000, 0010). * When the number of copies is designated, film sheets are printed in the quantity specified in a single printing operation. * This parameter is necessary when printing multiple sheets for a single data transfer operation. 	<ul style="list-style-type: none"> * This parameter is set according to the user's requirement. * In the DICOM library TYPE3, the value is transferred together with the Tag. However, if the value is unknown, the value is either transferred as a character string with length 0, or the element itself is not transferred. → The printer default values are used if this parameter is not entered.
-y priority Priority in the DICOM printer (HIGH/MED/LOW)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Film Session (2000, 0030). * This parameter determines where this transfer image is inserted into the queue in the DICOM printer. At HIGH, the image is printed first among the queued images. 	<ul style="list-style-type: none"> * This parameter is set according to the user's requirement. * In the DICOM library TYPE3, the value is transferred together with the Tag. However, if the value is unknown, the value is either transferred as a character string with length 0, or the element itself is not transferred. → The printer default values are used if this parameter is not entered. * Note this parameter does not determine where this transfer image is inserted into the CXDI queue.
-D destination Film destination (MAGAZINE/PROCESS OR/BIN_i)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Film Session (2000, 0040). * Film is sent to the output device designated by RECEIVE MAGAZINE or the automatic developer. 	<ul style="list-style-type: none"> → The printer default values are used if this parameter is not entered. * The film is usually discharged to the default output device.
-F film type Film media type (“BLUE FILM” / “CLEAR FILM” / “PAPER”)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Film Session (2000, 0030). * Film is printed as the designated film type. 	<ul style="list-style-type: none"> → The printer default values are used if this parameter is not entered. * Although many types of films cannot be detected, the film type can be selected in the KELP2180. * In this parameter, be sure to put quotation marks (“ ”) around 0x20 since it comes between BLUE and FILM.

2. Installation Manual

-L sessionLabel Film session label (character string)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Film Session (2000, 0050). * The label for the film session is for designation purposes only, and generally it is not displayed directly on the print image. 	<p>→ The parameter is not transferred over DICOM if it is not designated.</p> <ul style="list-style-type: none"> * This parameter may be displayed in some form or another depending on the installed printer. For example, it may be displayed in the Control Panel for the printer or in the corner of the film.
-f films Number of film box to be printed	<ul style="list-style-type: none"> * Currently, this parameter is not operating. 	
-i Format Format at print	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Film Box (2010, 0010). * This is not necessary, as for automatically designated on CXDI. 	<ul style="list-style-type: none"> * If this parameter is not designated, transfer software uses automatically STANDARD1 1, for reason this parameter must be transferred in the DICOM.
-l FilmSizeID Film size 14 inch x 17 inch / 17 inch x 14 inch / 11 inch x 14 inch / -l FilmSizeID / 10 inch x 14 inch 10 inch x 12 inch / 24 cm x 24 cm / 24 cm x 30 cm	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Film Box (2010, 0050). * This parameter designates the size of the film to be printed 	<p>→ The parameter is not transferred over DICOM if it is not designated. In this case, the printer default values are used. When this parameter is not transferred, problems can occur since unsuitable default values may be used.</p> <ul style="list-style-type: none"> * Some printers do not print until a supply magazine of the designated size is loaded, and others print even though the designated size is different from the currently loaded supply magazine.
-M magnification Interpolation method (NONE/REPLICATE/BILINEAR/CUBIC)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Film Box (2010, 0060). * This parameter designates the interpolation method since the printer has a higher resolution than the CXDI in most cases. * Generally, CUBIC provides the best results, followed by BILINEAR. The REPLICATE option is not suitable for CXDI image applications. 	<p>→ The printer default values are used if this parameter is not entered. When this parameter is not transferred, problems can occur since unsuitable default values may be used.</p>
-m smoothing Type of smoothing (character string)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Film Box (2010, 0080). * This parameter designates the smoothing method for the image. * In the DICOM standards, this parameter setting is valid only when CUBIC is selected for the magnification parameter above. * In the DICOM standards, value to be transferred is not predetermined. 	<p>→ The parameter is not transferred over DICOM if it is not designated. In this case, the printer default values are used. When this parameter is not transferred, problems can occur since unsuitable default values may be used.</p> <ul style="list-style-type: none"> * This parameter is determined by asking the printer engineer or by viewing the conformance statement.

2. Installation Manual

	<ul style="list-style-type: none"> * The designation method varies according to the printer. For example, the MLP190 uses -m NORMAL. * This parameter is used in the DICOM Basic Film Box (2010, 0150). 	
-S configuration Adjustment information (character string)	<ul style="list-style-type: none"> * This parameter sets the printer (image quality) adjustment from the SCU side. * In the DICOM standards, value to be transferred is not predetermined. * The designation method varies according to the printer. * This parameter is used in the DICOM Basic Film Box (2010, 0040). 	<p>→ If this parameter is not designated, it is not transferred over DICOM. In this case, the printer default values are used. When this parameter is not transferred, problems can occur since unsuitable default values may be used.</p> <p>* This parameter is determined by asking the printer engineer or by viewing the conformance statement.</p>
-O Orientation Film orientation (PORTRAIT/LANDSCAP E)	<ul style="list-style-type: none"> * In versions before 2.0, printers must operate based on this parameter. * When using image cutout from 17 x 17 inch size in the CXDI, this parameter is set and transferred automatically. * This parameter is used in the DICOM Basic Film Box (2010, 0130). 	<p>→ If this parameter is not designated, it is not transferred over DICOM. In this case, the printer default values are used.</p> <p>* Starting from version 2.0, the image can be rotated from the CXDI side without using this parameter.</p>
-A max_density Maximum density (Dx100)	<ul style="list-style-type: none"> * This parameter designates the density of the digital value for 0 (4095 for reverse display) of the CXDI transfer data image pixels. (In the CXDI, 0 indicates black.) * In the CXDI, this parameter is used to adjust the density. Therefore, be sure to always check that it is operating. 	<p>→ If this parameter is not designated, it is not transferred over DICOM. In this case, the printer default values are used. When this parameter is not transferred, problems can occur since unsuitable default values may be used.</p>
-a min_density Minimum density (Dx100)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Film Box (2010, 0120). * This parameter designates the density of the digital value for 4095 (0 for reverse display) of the CXDI transfer data image pixels. (In the CXDI, 4095 indicates white.) * This parameter is not transferred in many cases since the minimum density cannot be increased in most printers. 	<p>→ If this parameter is not designated, it is not transferred over DICOM. In this case, the printer default values are used. When this parameter is not transferred, problems can occur since unsuitable default values may be used.</p>

2. Installation Manual

-B border_density Border density (Dx100) (BLACK/WHITE/D x 100)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Film Box (2010, 0100). * This parameter determines the area density around the image on the film. 	→ If this parameter is not designated, it is not transferred over DICOM. In this case, the printer default values are used.
-G empty_image_density Empty image density (BLACK/WHITE/D x 100)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Film Box (2010, 0110). <p>This parameter designates the density of the empty image area during multi-formatting.</p>	→ If this parameter is not designated, it is not transferred over DICOM. In this case, the printer default values are used.
-T trim Trimming (NO/YES)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Film Box (2010, 0140). * This parameter adds lines around the image. * The CXDI is normally adjusted so that the trimming does not appear. 	<p>→ If this parameter is not designated, it is not transferred over DICOM. In this case, the printer default values are used.</p> <p>* For example, the default value for this parameter in Agfa printers is YES. Therefore, the NO option needs to be specifically designated if it is desired.</p>
-P polarity Polarity (NORMAL/REVERSE)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Image Box (2020, 0020). * Reverse image density 	→ If this parameter is not designated, it is not transferred over DICOM. In this case, the printer default values are used.
-r pixel_pitch Transfer pixel pitch for designating the request image size (Pixel Pitch in um)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Image Box (2020, 0020). * Reverse image density * This parameter is used in the DICOM Basic Image Box (2020, 0010). * Position of the image on film * The cumulative value for the horizontal size of the image (raw) at the designated pixel pitch is used for the request image size. * The CXDI automatically uses 131072 internally for operation. * The above value can be overwritten by designating a specific value. 	→ If this parameter is not designated, it is not transferred over DICOM. In this case, the type of image that is printed depends on the settings at the printer side.
-N annoFmt Annotation position (1/2/3)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Annotation Box (2030, 0010). * This parameter designates the position of the character string to be annotated. 	* If using annotation, always be sure to transfer the annotation position.
-n annotation Annotation (character string)	<ul style="list-style-type: none"> * This parameter is used in the DICOM Basic Annotation Box (2030, 0020). * This parameter designates the character string to be annotated. 	<p>* If this parameter is not designated, it is not transferred over DICOM. In this case, the printer default values are used.</p> <p>* Also, in this case, the type of image that is printed depends on the settings at the printer side.</p>

2. Installation Manual

-u maxPDU Maximum PDU value in byte units	<ul style="list-style-type: none"> * The CXDI automatically uses 131072 internally for operation. * The above value can be overwritten by designating a specific value. 	<ul style="list-style-type: none"> * The DICOM standards do not allow values of 1301073 or higher to be set. * This parameter is used when the operator of the connected storage device requests a size change. * In DICOM storage devices, note that the argument title changes to -m. (→See the storage device parameters.)
-t callingTitle Called App Entity Title	<ul style="list-style-type: none"> * The AE Title setting field is automatically used in this setting. * The above value can be overwritten by designating a specific value. 	<ul style="list-style-type: none"> * Note that the meaning is opposite of the argument -c for DICOM storage devices. (→See the storage device parameters.) * The entry for the OPU output device title is used here.
-t callingTitle Calling App Entity Title	<ul style="list-style-type: none"> * The CXDI automatically uses CANON_CCR internally for the operation. * The above value can be overwritten by designating a specific value. 	<ul style="list-style-type: none"> * Note that the meaning is opposite of the argument -t for DICOM storage devices. (→See the storage device parameters.)
-g N-GET Printer compatibility mode	<ul style="list-style-type: none"> * This parameter is used simply as “-g”. * In the CXDI default settings, the printer information is not designated. In this case, the printer side sends all the information that it has (DICOM official specifications). * When the -g option is added, the essential information only is collected. This information includes the Printer Status and Printer Status Info. (To prevent installation when the printer does not satisfy the above DICOM specifications.) 	<p>→ Normally, this option is not used. This parameter has been provided as a remedy when a printer error occurs when optional devices are not used.</p>
-S Silent mode	<ul style="list-style-type: none"> * This parameter is used simply as “-s”. * This parameter is used to prevent the transfer software from displaying the debugging character string on the console. 	<ul style="list-style-type: none"> * This parameter does not affect DICOM data transfer. → Silent mode does not need to be designated since the CXDI automatically makes the setting internally.
-p This parameter dumps the association parameter.	<ul style="list-style-type: none"> * This parameter is used simply as “-p”. * This parameter is used to set the transfer software so that the debugging character string is displayed on the console. 	<ul style="list-style-type: none"> * This parameter does not affect DICOM data transfer.
-v This parameter dumps the transfer log.	<ul style="list-style-type: none"> * This parameter is used simply as “-v” * This parameter is used to set the transfer software so that the debugging character string is displayed on the console. 	<ul style="list-style-type: none"> * This parameter does not affect DICOM data transfer.

2. Installation Manual

	* Both the -p and -v parameters should be used. These settings override the -s parameter.	
-V filename This parameter dumps the transfer log.	* The parameter is used for analysis after the transfer software saves the debugging character string displayed on the console to a file with a designated filename. It is used only when problems occur.	* This parameter does not affect DICOM data transfer.
-I A-RELEASE-RES is ignored.	* This parameter is used simply as "-I"	* This is used when the error message [30012 Peer aborted Association (or never connected)] occurs even though the DICOM data transfer was successful. → This is used based on the connected printers.
-jn This is the time to take timeout.	* Sets the time to take timeout in seconds.	* This parameter is to be changed when taking timeout.

Note

The parameters -p, -v, and -V filename display the log on the console. Therefore, be sure to always erase these parameters before operation by the user.

2. Installation Manual

Examples of parameters used with different makers and types of printers (reference)

Name	Default Parameters	Significance
Kodak MLP190	-A 320 -T NO -M CUBIC -m NORMAL -S CS000 (entered in param member) 80 (entered in pixelPitch member) 14 x 17 4096 (entered in W member) 5120 (entered in H member)	<ul style="list-style-type: none"> • Trimming OFF • Cubic spline interpolation • Smoothing: normal • Maximum density: 3.20 • Curve shape 0 (density linear) as Config Info
Kodak KELP2180 + Kodak Print Spooler Model 100	-A 320 -T NO -M CUBIC -m NORMAL -S CS000 (entered in param member) 79 (entered in pixelPitch member) 14 x 17 4090 (entered in W member) 5120 (entered in H member) 11 x 14 3194 (entered in W member) 4096 (entered in H member)	<ul style="list-style-type: none"> • Trimming OFF • Cubic spline interpolation • Smoothing: normal • Maximum density: 3.20 • Curve shape 0 (density linear) as Config Info
Agfa DryStar 3000	-A 320 -T NO -M CUBIC -m 140 -S “PERCEPTION_LUT=200” (entered in param member) 80 (entered in pixelPitch member) 14x17 4256 (entered in W member) 5174 (entered in H member)	<ul style="list-style-type: none"> • Trimming OFF • Cubic spline interpolation • Smoothing: slightly sharp (edges emphasized) • Maximum density: 3.20 • S “PERCEPTION_LUT=200(LINEAR)” (If the output fails to be linear with “LINEAR”, on-site adjustments with the printer manufacturer must be performed.
Kodak Imation DryView 8700 + Pacs LINK IMN 9410	-A 310 -T NO -M CUBIC -m ? -S LUT=0?, 2? (? : Site Dependent) (entered in param member) 78 (entered in pixelPitch member) 14x17 4096 (entered in W member) 5220 (entered in H member)	<ul style="list-style-type: none"> • Trimming OFF • Cubic spline interpolation • Smoothing must be adjusted at the user’s site. • Maximum density: 3.10 • S LUT = m, n is designated as the Config Info but m and n are adjusted on-site by the Kodak service engineer. Basically, adjustment is performed to achieve a linear output.
Kodak Imation DryView 8700 + GW	-A 310 -T NO -M CUBIC -m ? -S LUT=?, ? (? : Site Dependent) (entered in param member) 78 (entered in pixelPitch member) 14x17 4096 (entered in W member) 5220 (entered in H member)	<ul style="list-style-type: none"> • Trimming OFF • Cubic spline interpolation • Smoothing must be adjusted at the user’s site. • Maximum density: 3.10 • S LUT = m, n is designated as the Config Info but m and n are adjusted on-site by the Kodak service engineer. Basically, adjustment is performed to achieve a linear output.
Kodak Imation DryView 8700+8800	-A 320 -T NO -M CUBIC -S “LUT=m, n”-m (on-site adjustment) (entered in param member) 78 (entered in pixelPitch member) 4096 (entered in W member) 5220 (entered in H member)	<ul style="list-style-type: none"> • Trimming OFF • Cubic spline interpolation • Maximum density: 3.20 • S LUT = m, n is designated as the Config Info but m and n are adjusted on-site by the Kodak service engineer. Basically, adjustment is performed to achieve a linear output.

2. Installation Manual

		<ul style="list-style-type: none"> • The Kodak service engineer is responsible for setting the smoothing type on-site since it can be changed with each printer. • The rest is done by the printer itself.
Kodak Imation DryView 8700+9440	-A 320 -T NO -M CUBIC -S “LUT=m, n”-m (on-site adjustment) (entered in param member) 78 (entered in pixelPitch member) 4096 (entered in W member) 5220 (entered in H member) The model 8800 has a rotation function but we understand that Imation has not publicly acknowledged the use of this function.	<ul style="list-style-type: none"> • Trimming OFF • Cubic spline interpolation • Maximum density: 3.20 • S LUT = m, n is designated as the Config Info but m and n are adjusted on-site by the Kodak service engineer. Basically, adjustment is performed to achieve a linear output. • The Kodak service engineer is responsible for setting the smoothing type on-site since it can be changed with each printer. • The rest is done by the printer itself.
Kodak Imation Dry View 8500+	-A 310 -T NO -M CUBIC -m ? -S LUT=0?, 2? (? : Site Dependent) (entered in param member) 78 (entered in pixelPitch member) 14x17 3388 (entered in W member) 4277 (entered in H member)	<ul style="list-style-type: none"> • Trimming OFF • Cubic spline interpolation • Smoothing must be adjusted at the user’s site. • Maximum density: 3.10 • -S • LUT = m, n is designated as the Config Info but m and n are adjusted on-site by the Kodak service engineer. Basically, adjustment is performed to achieve a linear output.
Nishimoto EL2000N	-A 320 -T NO -M CUBIC -S 15 (entered in param member) 80 (entered in pixelPitch member) 4444 (entered in portraitW member) 5296 (entered in portraitH member) 5296 (entered in landscapeW member) 4444 (entered in landscapeH member) “Prepare images using CXDI” : Yes A simple calculation yields a resolution of 4444 x 5400 for the display area of the model EL2000. However, 5376@80 µm is set in the perpendicular direction of the model EL2000 since the maximum size of the CXDI images is 2688@160 µm. In this case, a small non-image area should be output as the border in the up/down direction on the film according to the calculation. In actual fact, however, the image will protrude in some cases depending on how the transport speed and other	<ul style="list-style-type: none"> • Trimming OFF • Cubic spline interpolation • Maximum density: 3.20 • “15” in Config Info is linear. • The rest is done by the printer itself. <p>Up to 5376 pixels can be set for H.</p>

2. Installation Manual

	<p>factors have been adjusted. The specifications are as follows although they cannot be set at the present time: 14" x 14" : W=4444, H=4444 (for portraits) 11" x 14" : W=4444, H=3660 (for portraits)</p>	
Fuji CR-DPL/LPD/FM-DPL + FN-PS551	<p>-A 300 -T NO -M CUBIC -m MEDIUM -S -P NORMAL -B BLACK -k 2 -S ? (Site Dependent) (entered in param member) 14x17 3520 (entered in W member) 4280 (entered in H member) 14x14 3520 (entered in W member) 3490 (entered in H member) 11x14 2540 (entered in W member) 3600 (entered in H member)</p>	<ul style="list-style-type: none"> • Trimming OFF • Cubic spline interpolation • SHARP, MEDIUM or SMOOTH can be selected from among the presettings as the smoothing type. An AVR of 0.8 or so is appropriate. The setting is performed for each printer on-site. • -S should be adjusted at the user's site. • LUT can be selected from among the eight presettings 1 through 8 using Config Info. The setting is performed for each printer on-site. • With -k 2, the Window Center/Level for DICOM TAG (0028,1050) and (0028, 1051) are also deleted. • Maximum density: 3.00 A density of 3.20 cannot be designated. For this reason, a non-linear LUT is required.
Konica Drypro 722 + Printlink	<p>-A 320 -T NO -M CUBIC -m 2 -S "KC_LUT=1" -O PORTRAIT -P NORMAL -B BLACK (entered in param member) 80 (entered in pixel pitch member) 14x17 4424 (entered in W member) 5324 (entered in H member) 14x14 4424 (entered in W member) 4372 (entered in H member) 11x14 3436 (entered in W member) 4424 (entered in H member)</p>	<ul style="list-style-type: none"> • Trimming OFF • Cubic spline interpolation • Smoothing type 1: BILINEAR 2: Sharp by spline interpolation 3: Slightly weak by spline interpolation 4: Weaker by spline interpolation • Maximum density: 3.20 Maximum density 3.20 could not be achieved before.
Konica Li-62P + Printlink	<p>-A 320 -T NO -M CUBIC -m 2 -S "KC_LUT=1" -O PORTRAIT -P NORMAL -B BLACK (entered in pixel pitch member) 14x17 4268 (entered in W member) 5108 (entered in H member) 14x14 4268 (entered in W member) 4104 (entered in H member) 11x14 3204 (entered in W member) 4268 (entered in H member)</p>	<ul style="list-style-type: none"> • Trimming OFF • Cubic spline interpolation • Smoothing type 1: BILINEAR 2: Sharp by spline interpolation 3: Slightly weak by spline interpolation 4: Weaker by spline interpolation • Maximum density: 3.20 Before, maximum density 3.20 could not be achieved.

2. Installation Manual

Printer Model Specifications (Reference)

Name	Specifications	Maximum equivalent area in CXDI
Kodak MLP190	80μm x 4096 x 5120	2048 x 2560 (@160 μm)
Kodak KELP2180 + Kodak Print Spooler Model 100	<p>79 μm x 4090 x 5120 (value after passing through the print spooler)</p> <ul style="list-style-type: none"> • The above settings are the size of the effective area when the image passes through the print spooler and the image is plotted up to the annotation area. In other words, these settings do not display an annotation area, instead handling it as an image area. • If the data is transferred without setting [Image creation in CXDI], the Requested Image Size setting is used in DICOM. In this case, the annotation area is automatically displayed in the 2180 printer. As a result, a maximum image area of 79 μm x 4090 x 4996 must be designated. In this case, the CXDI relies on the 2180 for image rotation (Film Orientation), but images larger than 1.7 MB cannot be rotated by the 2180. Therefore, operation without the setting for [Image creation in CXDI] cannot be performed in the 2180. (Although operation is possible by setting Requested Image Size only for using DICOM without the setting for [Image creation in CXDI], this option is not installed in the CXDI.) • Although the resolution of the printer itself is 79 μm x 4090 x 5260, this complete resolution cannot be used when the image passes through the spooler. When “_” is used in AE Title, the association is rejected. Use the Disable function for N-EVENT-REPORT to disable this setting. The FilmSize parameter can be used. The MediaType (BLUE, CLEAR) parameter is also supported. • Although the Film Orientation parameter is supported up to 1.7 MB, in actuality, DR images cannot be rotated. Like the DryView8700, the images must be rotated by the CXDI side. • When Requested Image Size is expanded, the maximum plotting size is limited (79 μm x 4090 x 4996) so that the annotation area can be obtained. When a Requested Image Size expansion error occurs, the image is interpolated and printed at the suitable size. In this case, the error does not return to the CXDI side. For example, the image is printed at 310 mm even if 326 mm is designated. • If an expansion error occurs in the spooler when Multi Display Format is used, the print queue cannot be processed. • The system is in a critical state when a Failure status is indicated. A user message is displayed indicating this state, and images are no longer transferred. (Fully installed) • During the Warning status, image transfer is performed while the user message is displayed (Fully installed). • If operation is aborted due to an error, a new association could not be established when the data was resent from the CXDI. GW was reset to recover the error. 	2018 x 2528(@160 μm)

2. Installation Manual

	<ul style="list-style-type: none"> • Inserting annotations in the image can lead to problems at the hospital. In the QCW, use annotations that are outside of the image. • The designated film size is 11 x 14 inch film, and automatic selection of the magazine and printing has been confirmed. • Annotations in the image are problematic in the US and EU. Thus, although DICOM annotation was used, it was not printed. Although annotation can be transferred without any errors in DICOM, an annotation error occurred in the log when transferring from the gateway to the 2180, and printing was not performed. Data was transferred from KCR to the validation tool, and the DICOM transfer method was compared to CXDI. However, the only differences were in the image size, aspect ratio, and annotation position. • Although the annotation position is 1 in terms of conformance, it is 0 as sent from KCR. The result did not change even after the change. 	
Agfa DryStar 3000	80 µm x 4256 x 5174 <ul style="list-style-type: none"> • In the standard Agfa system, the annotation option is selected. Therefore, the full image area will not be printed correctly unless you ask the serviceman to deselect the annotation option. 	2128 x 2587 (@160 µm)
Imation DryView 8700+8800	78 µm x 4096 x 5220 Note: The 8700 printer cannot display in landscape orientation. Also, the maximum density is 3.1. If the 8800 box is not added, this printer cannot be used by the CXDI. However, it can be used starting from CXDI version 2.0. <ul style="list-style-type: none"> • If there is an Imager Pixel Spacing tag (0018, 2264), the imager will fail. 	1996 x 2544 (@160 µm)
Fuji CR-DPL /FM-DPL + FM-PS551	100 µm x 3520 x 4280 (value after passing through the print spooler) <ul style="list-style-type: none"> • The above settings are the allowable area size in a configuration not using annotation. • Annotation will be supported from the next version. Annotation is currently possible in US-ASCII only. IDs are designated 1 to 6 and correspond to the top left, top center, top right, bottom left, bottom center, and bottom right, respectively. The maximum area size with annotation support is 3500 x 4170 for 35 cm x 43 cm and 2538 x 3522 for B4. • Use the Disable function for N-EVENT-REPORT to disable this setting. • A function is provided for disabling the returning of warning messages. 0107 (Attribute list error) Return/Not return 0116 (Attribute Value out of Range) Return/Not return B604 (Image has been demagnified) Return/Not return • The Film Size parameter can be used. The Media Type (BLUE, CLEAR) parameter can also be used. • The Film Orientation parameter is fully supported. • The following presets are made so that LUT has the 	2200 x 2675 (@160 µm)

2. Installation Manual

	<p>DMAX = 3.2D equivalent curve required by CXDI. Gamma type #17 (SAR system)</p> <p>Density Shift Contrast</p> <p>Point 1</p> <p>1.57 0.10 1.00</p> <p>Point 2</p> <p>2.29 0.15 1.00</p>	
--	---	--

2. Installation Manual

Error Return Values and Log Output for print_stuff (Reference)

Error example	Return value and log output
Success	Return value: 0x00 There is no log output in this case.
Invalid parameter	Return value: 0x00000001 CXDI description : DICOM connection error (CCRTRANS_ERR_DICOMPARAM) The log output in this case is shown below. ----- ** -s Silent mode; do not print results of all print commands ** -v Use verbose mode for DUL and SRV facilities ** x Canon Hidden Special Mode node The host name that is running a print server port TCP/IP port number of print server file One or more files that contain preformatted images for printing -----
The server has not started up.	Return value: 0x00180012 CXDI description : DICOM connection error (CCRTRANS_ERR_NOT_CONNECT) ----- The log output in this case is shown below. 18-135933[d2]ERR: d0012 Attempt to connect to unknown host: test 18-135933[d2]ERR: 130012 Peer aborted Association (or never connected) 18-135933[d2]ERR: 180012 Failed to establish association -----
After a command request was sent to the server, an error was returned in response.	Return value: 0x10 CXDI description: DICOM response error (CCRTRANS_ERR_RESP) The log output in this case is shown below. ----- (Not determined) -----
After a command request was sent to the server, a warning was returned in response.	Return value: 0x18 CXDI description : DICOM response warning (CCRTRANS_WRN_RESP) The transfer process was successful, but a warning was returned from the server. The log output in this case is shown below. ----- (Not determined) -----
The printer status has returned an error.	Return value: 0x20 CXDI description : DICOM printer status error (CCRTRANS_ERR_PRN_STATUS) The log output in this case is shown below. ----- (Not determined) -----

2. Installation Manual

<p>The printer status has returned a warning.</p>	<p>Return value: 0x28 CXDI description: DICOM printer status warning (CCRTRANS_WRN_PRN_STATUS) The transfer process was successful, but a warning was returned as the printer status. The log output in this case is shown below.</p> <p>----- (Not determined) -----</p>
<p>Other errors</p>	<p>Return value: Values other than those above CXDI description : DICOM communications error (CCRTRANS_ERR_DICOM_TRANSE) The log output in this case depends on the specific error. A typical example is shown below.</p> <p>----- 18-140933[d2]ERR : c0082 SRV Send (DATA SET) failed in SRV_SendDataSet 18-140933[d2]ERR : 190082 SRV Request failed in SRV_NCreateRequest 18-140933[d2]ERR : 70012 NULL_key passed to routineDUL_ReleaseAssociation -----</p>

2. Installation Manual

Precautions for connecting the server (reference)

Equipment	Restrictions on connections
Kodak Miil	Transmitting the 0019 shadow group causes a failure, and the group is not received properly with the default. Its reception is enabled by setting the strictValidation parameter to Off in Miil.
Fujitsu Dr. ABLE	<ul style="list-style-type: none"> Transmission is currently performed with the “1 study multi series/1 series 1 image” setting. However, since a multi format is used for the screen displays for each series under the Dr.ABLE specifications, the switching operations are a hassle. The user will find it more convenient if it is at all possible to change the setting to “1 study 1 series/1 series multi image.” (These unusual data specifications were requested with the full understanding of their unusualness.) With DICOM, the body parts (such as the abdomen and head) and their directions (such as PA and AP) belong to the series information. It therefore follows that a different series is required for a different body part or body part direction. This aspect is restricted by the DICOM standard rather than by the installation and other steps taken by us. To put it the other way around, multiple images with different body parts and their directions cannot be put together as a series. To remedy this problem, devising a way of enabling the viewers to reference different series at the same time at some future point in time will be helpful.
Hitachi	<ul style="list-style-type: none"> Transmission is currently performed with the “1 study multi series/1 series 1 image” setting. However, since a multi format is used for the screen displays for each series, the switching operations are a hassle. The user will find it more convenient if it is at all possible to change the setting to “1 study 1 series/1 series multi image.” This problem arises with the Fujitsu equipment as well. Refer to the section on Fujitsu.

send_image error return values and log output (reference)

Example of error	Return value and log output
Successful	Return value: 0x00 No log output at this time
Invalid parameter exists.	Return value: 0x00000001 CXDI interpretation: DICOM connect error (CCRTRANS_ERR_DICOMPARAM) See below for the log output at this time: ----- -t Set called AE title to title in Association RQ -v Place DUL and SRV facilities in verbose mode node Node name for network connection port TCP / IP port number of server application image A list of one or more images to send -----
Server fails to start.	Return value: 0x00180012 CXDI interpretation: DICOM connection error (CCRTRANS_ERR_NOT_CONNECT) See below for the log output at this time: ----- 18-132600[127]ERR: 60012 TCP Initialization Error: Invalid argument 18-132600[127]ERR: 130012 Peer aborted Association (or never connected) 18-132600[127]ERR: 180012 Failed to establish association -----
As a result of providing the server with a command request, an error was returned as response.	Return value: 0x10 CXDI interpretation: DICOM response error (CCRTRANS_ERR_RESP) See below for the log output at this time: ----- (To be determined) -----

2. Installation Manual

<p>As a result of providing the server with a command request, a warning was returned as response.</p>	<p>Return value: 0x18 CXDI interpretation: DICOM response warning (CCRTRANS_WRN_RESP) The transmission processing was successful but a warning was returned from the server. See below for the log output at this time: ----- (To be determined) -----</p>
<p>Other errors</p>	<p>Return value: other than above CXDI interpretation: DICOM communication error (CCRTRANS_ERR_DICOM_TRANSE) The log output is many and varied. It depends on the error. One example is shown below. ----- 18-140933[d2]ERR: c0082 SRV Send (DATA SET) failed in SRV_SendDataSet 18-140933[d2]ERR: 190082 SRV Request failed in SRV_NCreateRequest 18-140933[d2]ERR: 70012 NULL key passed to routine: DUL_ReleaseAssociation -----</p>

2. Installation Manual

Concerning the Dry View 8700 (reference)

LUT (Lookup Table)

- Image adjustment parameters that can be changed by users

Density : This can be set up to the maximum density of 3.1D.

Contrast : This can be set from 1 to 15.

- Image adjustment parameters that cannot be changed by users

Lookup tables called TFTs (Transfer Function Tables) are provided internally, and changes can be made only in the service mode.

Fifteen types of characteristic curves are registered in one of these TFTs, and users can change one of these curves as the contrast.

Over 30 TFTs are registered in the printer, and a name is allocated to each one.

For instance, 15 types of linear straight lines are registered in the TFT called "WRKST2A."

By setting this WRKST2A TFT, adjustments can be made by combining 15 types of linear straight lines (which cannot be changed by users) with 15 types of characteristic curves (which can be changed by users).

Concerning connections

Two types of the Dry View 8700 are available.

- Dry View 8700 Plus

The 8700 Plus is a printer which can be connected to two diagnostic units. When used in combination with the 8800 multi input manager, it can be connected to up to eight diagnostic units. Images are processed as described above.

- Dry View 8700 Dual

It is possible to connect two 8700 Dual units to the 8800 multi input manager. By using these in combination, up to seven diagnostic units can be connected. The 8700 Dual does not come with image processing functions

Modality connection I/F


This I/F is the external interface which connects "Dry View 8700" with each modality. Select the following item depending on the modality which would be connected.

- Digital Signal: DEIB (Digital External Interface Box)
- Video Signal: EVEIB (Enhanced Video External Interface Box)
- Keypad, Auto Filming: UKEIB (Universal Keypad External Interface Box)

2. Installation Manual


Dry View 8700 Plus

Up to 2 units can be connected.



Dry View 8700 Plus + 8800 Multi Input Manager


Up to 8 units can be connected.



Dry View 8700 Dual + 8800 Multi Input Manager

Up to 2 printers can be connected
(only with Dry View 8700 Dual)

Up to 7 units can be connected.



2. Installation Manual

(11) Linearity Check of Transfer Image Density

1) Purpose

An SMPTE image is used to check whether the density linearity of the image printed out by the printer and the image displayed on the high-definition monitor matches the density linearity of the image transferred by the CXDI.

2) Notes

2-1) This checking procedure should be performed before the procedure in the section of “Operation Unit Gamma Correction”.

2-2) The adjustment and checking procedures below should be completed before performing this procedure.

A) The printer and high-definition monitor connections and setting adjustments should be completed. The printer and monitor image output settings should be set to LINEAR.

For example, if the KODAK MLP190 is connected, the printer parameter “-S configuration” must be set to “-S CS000”. For other printers, refer to “Printers and Parameter Examples Reference” in “Network Connections”, and set so that the curve shape is 0 (density linear).

B) Be sure to calibrate the printer and high-definition monitor units separately before performing this procedure.


C) When the imaging screen is “tray type”, change it to “category type” by selecting:
System → SETUP MENU → CUSTOMIZE DISPLAY.

3) Rough adjustment

3-1) Start up the CXDI system.

3-2) Using the two knobs at the rear of the operation unit, adjust the brightness and contrast of the touch panel screen for optimum visibility.


3-3) On the exposure screen, select the exposure mode “SMPTE” and wait until “READY” appears. [Fig. 1]



[Fig. 1]

2. Installation Manual

- 3-4) Press the exposure switch on the X-ray generator, and after the exposure, press the END STUDY button. Transfer the SMPTE pattern image to the printer or the high-definition monitor. [Fig. 2]




[Fig. 2]

- 3-5) Measure the densities of the 11 locations (0% to 100%) of test image grayscale on the film or on the monitor. [Fig. 3]

* Measure the SMPTE image density on the film is measured using a densitometer.

Measure the SMPTE image density on the high-definition monitor using the gradation analysis software.


* The data for the SMPTE test image grayscale transferred by the CXDI are the values for the maximum density (3.20 in the case of the MLP 190) in the printer settings which have been changed in 11 uniform steps.



[Fig. 3]

2. Installation Manual

3-6) Create the graph below based on the data measured in step 5).



As shown in the above graph, the measurement values need only to nearly form a straight line from the minimum density to the maximum density.

The important point here is that the measurement values make a straight line and a maximum density corresponding to the settings is output.

If the measurement values deviate too far from the straight line and a maximum density corresponding to the settings is not output, printer and monitor output linearity settings, calibration, and other adjustments are necessary.

* The above graph is an example of measurements when the maximum density is set to 3.2 D and the printed film is measured with a densitometer. Refer to the data below when the maximum density is set to 3.1 D, or when gradation analysis software is used to take measurements on the monitor.

* The LINEAR output cannot be set for some printer models.

In this case, try to select an output setting as close as possible to LINEAR.

Ideal density values in LINEAR LINE

Step	1	2	3	4	5	6	7	8	9	10	11
3.2 D	0	0.32	0.64	0.96	1.28	1.60	1.92	2.24	2.56	2.88	3.20
3.1 D	0	0.31	0.62	0.93	1.24	1.55	1.86	2.17	2.48	2.79	3.10
12 Bit	0	410	819	1229	1638	2048	2457	2867	3276	3686	4095
8 Bit	0	26	51	77	102	128	153	179	204	230	255


Possible causes of non-linearity in measurement values:

- * Inadequate calibration of printer and high-definition monitor
- * Inadequate settings for CXDI printer parameters
- * Faults in printer or high-definition monitor

2. Installation Manual

4) Fine adjustment

- 4-1) As the step (3)-3) above, make the system “READY” by selecting the exposure mode “SMPTE” on the exposure screen. [Fig. 4]




[Fig. 4]

- 4-2) On the X-ray generator press the exposure button. After the exposure, adjust the trim so that the gray scale may be located in the center of the image. [Fig. 5]

* For correct density measurement of the 32-step chart, the gray scale must be printed in the center of an image to eliminate the shading feature.


* Data may not from a straight line near the minimum and maximum densities due to characteristics of the printer. Rotate the image on the QA screen, and reprint or retake measurements.



[Fig. 5]

2. Installation Manual


- 4-3) Select the END STUDY and transfer the SMPTE pattern image to the printer or the high-definition monitor. [Fig. 6]



[Fig. 6]

- 4-4) On a printed film or on the monitor, measure the density of 32 steps of the grayscale on the test image. [Fig. 7]

- *1: Measure the SMPTE image density on the film using a densitometer. The SMPTE image density on the high-definition monitor is measured using the gradation analysis software.
- *2: The data for the SMPTE test image grayscale transferred by the CXDI are the values for the maximum density (3.20 in the case of the MLP 190) in the printer settings which have been changed into 32 uniform steps.




[Fig. 7]

2. Installation Manual

- 4-5) As the step (3)-6), create a graph based on the data measured in step 4), and make sure that the data from the minimum density to the maximum density nearly form a straight line.

Characteristics of the printer may prevent the data from forming a straight line near the minimum and maximum densities. Rotate the image on the QA screen, and reprint or retake measurements.



Ideal Density Data for Linear Line

Step	1	2	3	4	5	6	7	8	9	10	11
3.2 D	0	0.10	0.21	0.31	0.41	0.52	0.62	0.72	0.83	0.93	1.03
3.1 D	0	0.10	0.20	0.30	0.40	0.50	0.60	0.70	0.80	0.90	1.00
12 Bit	0	132	264	396	528	660	792	924	1056	1188	1320
8 Bit	0	8	16	24	32	41	49	57	65	74	82

Step	12	13	14	15	16	17	18	19	20	21	22
3.2 D	1.14	1.24	1.34	1.45	1.55	1.65	1.75	1.86	1.96	2.06	2.17
3.1 D	1.10	1.20	1.30	1.40	1.50	1.60	1.70	1.80	1.90	2.00	2.10
12 Bit	1453	1585	1717	1849	1981	2113	2245	2377	2509	2641	2774
8 Bit	90	98	106	114	122	131	139	147	155	164	172

Step	23	24	25	26	27	28	29	30	31	32
3.2 D	2.27	2.37	2.48	2.58	2.68	2.79	2.89	2.99	3.10	3.20
3.1 D	2.20	2.30	2.40	2.50	2.60	2.70	2.80	2.90	3.00	3.10
12 Bit	2906	3038	3170	3302	3434	3566	3698	3830	3962	4095
8 Bit	180	188	196	205	213	221	229	238	246	255

2. Installation Manual


<Reference 1>

In the data and graph below, the data was obtained by setting the Kodak MLP 190 to curve shape 0 (density linear), a maximum density of 3.20, the SMPTE test image was printed out, and the image data was measured.

As shown in the graph, the data from the minimum density (film base density) to the maximum density nearly form a straight line.

SMPTE Density_____

Step	1	2	3	4	5	6	7	8	9	10	11
Percentage	0	10	20	30	40	50	60	70	80	90	100
Density (D)	0.17	0.46	0.75	1.03	1.36	1.66	1.98	2.29	2.59	2.90	3.20



* The printer parameter settings in this case are:

-A 320 -T NO -M CUBIC -m NORMAL -S CS000

2. Installation Manual

<Reference 2>

Example when the graph does not form a straight line

In the data and graph below, the data was obtained by using the Kodak MLP 190 to print out the SMPTE test image, and the image data was measured.


(1): Shows normal data.

(2): Shows the case when the CXDI printer parameters are not set linearly.

(3): Shows the case when the printer was not calibrated properly.

SMPTE Density

Step	1	2	3	4	5	6	7	8	9	10	11
Percentage	0	10	20	30	40	50	60	70	80	90	100
(1) Normal	0.17	0.46	0.75	1.03	1.36	1.66	1.98	2.29	2.59	2.90	3.20
(2) Inadequate parameter settings	0.17	0.29	0.45	0.61	0.80	1.02	1.26	1.59	2.02	2.53	3.19
(3) Inadequate	0.17	0.33	0.55	0.81	1.08	1.36	1.66	1.97	2.28	2.59	2.94



* For improper parameters, the printer parameter “-S CS000” was not entered.

* For the inadequate calibration, the printer calibration data was set too low.

2. Installation Manual

(12) Operation Unit Gamma Correction

1) Purpose

This procedure is performed so that the image that is printed out or displayed on a high-definition monitor conforms exactly to the exposure image on the operation unit.

2) Notes

2-1) The procedure in “Linearity Check of Transfer Image Density” must be completed.

2-2) If image adjustment for the printer or high-definition monitor has not been made, use the “Gamma Correction Calculation Tool” in order to correct the gamma of high definition monitor image to be a same as printer image.

2-3) Gamma correction is an image correction process for monitors and film. It is different from the contrast setting or grayscale setting.

This procedure is simply a visual adjustment. As a result, differences may occur depending on the operator performing the procedure. Therefore, be sure to consult with the responsible technician before performing this adjustment.

2-4) To make the gamma of operation unit adjust in detail, use the “Gamma Correction Calculation Tool”.

3) Preparation

The Option button used in gamma correction is normally hidden. Edit the MenuPara.ini file to display.

3-1) Open MenuPara.ini file.

3-2) Make the following changes, and overwrite the file.

Use Search in Edit to find OptionDlgBth.


Select Customize.

OptionDlgBtn = 0 ← Change to 1.

(0: Don't display; 1: Display)


2. Installation Manual

- 4) Comparison of operation unit image and print image or monitor image.
 - 4-1) Start up the CXDI system.
 - 4-2) Use the two adjustment knobs at the rear of the operation unit to adjust the brightness and contrast of the touch panel screen for optimum visibility.
 - 4-3) On the exposure screen, select the exposure mode “SMPTE” and wait until “READY” appears. [Fig. 1].



[Fig. 1]

- 4-4) On the X-ray generator, press the exposure button, and after the exposure, select “END STUDY”. Transfer the SMPTE pattern image to the printer or the high-definition monitor. [Fig. 2]



[Fig. 2]

- 4-5) Take the SMPTE pattern image again. On the QA screen, compare the image displayed on the operation unit screen with the film image printed in Step 4) above or with the image on the high-definition monitor. Make sure there is no difference in contrast and gradation between those images. Check both preview and magnify images.


If there are any differences between these images, perform the procedure described in “(4) Operation Unit Image Gamma Correction” on the next page.

If there are no differences between these images, the steps are complete.

2. Installation Manual

5) Operation Unit Image Gamma Correction

- 5-1) On the QA screen displayed on Step (4) 5) above, select the “Option” tab and the “Gamma Adjustment” button is appeared, and then press this button. [Fig. 3]



[Fig. 3]

- 5-2) The “Gamma Adjustment” window appears. Change the value for the PREVIEW IMAGE, and press OK. The gamma correction for the operation unit screen is performed. [Fig. 4]

(Make sure the gamma value for the test image has changed on the operation unit screen.)

The gamma value is adjustable from 1.00 to 2.50.

When the image on the operation unit is lighter (whiter) than the film image, increase the value. On the contrary, if the image on the operation unit is darker (blackier) than the film image, decrease the value. The default gamma value is 1.60.



[Fig. 4]

- 5-3) When the gamma value for the preview image is adjusted, then adjust the gamma value for the magnify image. The default gamma value for the magnify image is 1.60.
- 5-4) The correction steps are complete.

2. Installation Manual

(13) Changing the Total Image Count

1) Purpose

When the imaging unit is replaced (including the replacement of the LANMIT) for servicing, the total image count displayed on the user screen can be returned to "0" if necessary.


2) Notes

- 2-1) The CXDI is connected by the system.
- 2-2) Set the CXDI application so that it does not start up.
- 2-3) Files are overwritten, and so be careful when performing the procedure.
- 2-4) As an extra precaution, write down the numerical values before overwriting them.
- 2-5) The overwritten counter becomes valid the next time that the CXDI is started up.

3) Procedure

- 3-1) Turn on the control computer, and then start up Windows XP.
- 3-2) Right click on My Computer on the Desktop screen of Windows XP, and open Explorer.
- 3-3) A file called "ExpResult.ini" is contained in the CCR folder.

Open this file. (D:\CCR\ExpResult.ini) [Fig 1]



[Fig 1]

2. Installation Manual

3-4) Changing the items below contained in the file allows you to change the settings for the counter in the user screen.

ExpResult.ini file	Screen Display	Note
[SystemCounter]		
TotalStudy=	TOTAL STUDIES	
UsrStudyCounter=	STUDY COUNTER	Can be overwritten at the user screen
UsrExposure Counter=	IMAGE COUNTER	Can be overwritten at the user screen
[LastCounterReset]		
StudyCounter=	Year, month, day, hour, minute	
ExpCounter=	Year, month, day, hour, minute	
[COUNTER 0]		
TotalCount=	Total number of images obtained with sensor unit 1.	
[COUNTER1]		
TotalCount=	Total number of images obtained with sensor unit 2.	
[COUNTER2]		
TotalCount=	Total number of images obtained with sensor unit 3.	
[COUNTER3]		
TotalCount=	Total number of images obtained with sensor unit 4.	

3-5) After overwriting the values, overwrite the file “ExpResult.ini” and save.

3-6) Close all windows that are open on the Desktop, and then start up the CXDI application.

3-7) Open the “System Information” screen, and check that the changed items have been set correctly. [Fig 2]

“TOTAL IMAGES” indicates the total number of images obtained with all sensors automatically.



[Fig 2]

2. Installation Manual

(14) Backing Up When Installing

1) Purpose

In case of re-installing the CXDI application, the necessary files ex) the exposure position and other parameters must be backed up so that can be restored at the status of first installation.

2) Necessary items

2-1) Removable drive such as MO drive or external HDD that can connect to USB 2.0

3) Notes

3-1) Before performing backup procedure, delete any “BodyPart” and image data exposed for tests.

Deleting image data: Refer to the “Deleting Data” item.

Deleting “BodyPart”: Refer to the CXDI Series Operation Manual.

3-2) Backup should be performed immediately before handing over the product to the customer only for new installations.

4) Connections

4-1) Check that all equipment is turned off.

4-2) Connect the keyboard and mouse removal drive to the control PC.

5) Settings

5-1) Turn on the operation unit power and then the control PC power.


5-2) The CXDI application starts. Press the [Alt] + [Tab] keys to switch the program to the Command Prompt screen.

5-3) The message “Welcome to Canon CXDI” appears. Input [8] and press the [Enter] key. (Select “8 Exit”.)

5-4) The Windows XP desktop screen appears.

5-5) Right click on My Computer on the Desktop screen, and select Explorer from Menu.

5-6) Explorer appears. Copy the CCR folder onto Removable Drive.



2. Installation Manual

(15) Backing up Setting Data to FD

1) Purpose

“Important setting data (setting information which differs for each customer.)” is backed up to floppy disks and hard disks in consideration of possible setting data loss, hard disk corruption or other data errors.

In the event that setting data is lost or the hard disk is corrupted, this “Important setting data” can be quickly restored to the condition before the trouble occurred by copying from the backup data.

2) Notes

2-1) Performing this backup work means that the CXDI system will be used with the floppy disk inserted in the floppy disk drive.

Be sure to eject the floppy disk from floppy disk drive in order to avoid damaging it, in case of changing the layout or moving the control PC.

Likewise, when mounting the system in a vehicle, vibrations may cause damage to the floppy disk drive.

Therefore, after backing up the latest data to the floppy disk, be sure to eject the floppy disk.

2-2) Based on the reason in note 1) above, do not perform backups in an environment that is exposed to vibrations. Therefore, never perform backups when the control PC is loaded in a car.

In V4.0 and later versions, the default FD-Buck Up setting is ON. When backup to a floppy disk is not allowed, set it to OFF.

2-3) In the product default settings, “Boot/1. Removable Device” in the system BIOS settings is set to “Disabled”. However, as a precaution, check that “Boot/1. Removable Device” is actually set to “Disabled”. If the setting is changed to “Legacy Floppy”, the control PC may not start properly when a floppy disk is inserted.

For more information, see “System BIOS Settings”

2-4) Be sure to always format the floppy disk that you are using before performing backups.

2-5) The backup procedure described here covers the case when backing up for the first time after installation. For the second and subsequent times, data is automatically backed up to the floppy disk whenever the user changes the exposure mode buttons or other settings.

2-6) This backup procedure cannot be performed with just the control PC. Connect the imaging units and other equipment, and start up in the normal exposure status.

3) Procedure

3-1) Remove the left side cover of the control PC.

3-2) Insert a formatted floppy disk (1.44 MB) in the floppy disk drive.

* Make sure the write protect of the floppy disk is unlocked at this time.

3-3) Reattach the left side cover of the control PC.

3-4) Start up the CXDI system. If you have changed the parameters including the exposure mode button, back up all “.ini.files” to a floppy disk when you restart the system again.

* When you first back up the files, the back up operation may take some time because there are many files to be copied.

3-5) Make sure that all files have been copied and switch off the CXDI system.

The files copied to a floppy disk are the “C:\ccrbup”, and they are the latest backup data. If the data stored in the drive D is damaged and there is no trouble in the drive C, restore the CXDI setting data using the data in “C:\ccrbup”.

2. Installation Manual

(16) Tool Modes (/np mode)

1) Purpose

The tool modes (startup options) are intended in order to check operation, and are used to launch the CXDI application on the control PC by itself, and to display items that are not normally displayed.

2) Notes

The following operation must be performed before using the “/np” mode. Especially, be sure to back up the exposure mode names and the customized settings before the operation.

2-1) When using “/np” with the same settings as that of the connected sensor unit

“BodyPart**.ini” file can be used as it is.

Example:

	Connection	/np setting
Sensor1	Table	Table
Sensor2	Stand	Stand

2-2) In case of using “/np” with different settings from that of the connected sensor unit

Move the “BodyPart**.ini” file in the “BodyParts” folder to the desktop, etc. However, do not move the Reference folder. If the “BodyPart**.ini” file is left in the “BodyParts” folder, system will not be able to be started, as the sensor type of the “BodyPart” and the settings do not match.

Example:

	Connection	/np setting
Sensor1	Table	Table
Sensor2	Stand	Stand

3) Preparation

3-1) Connect the keyboard and the mouse to the control PC.

3-2) Delete the “ccrstart.bat” file from startup.

3-3) Disconnect the imaging unit from the control PC.

4) Startup method

4-1) Start up Windows XP.

4-2) Start the Command Prompt screen.

Start ⇒ Program ⇒ Accessories ⇒ Command Prompt

4-3) Command Prompt screen appears, type the commands following instruction below to start the CXDI application. (Press the [Enter] key after typing the command.)

No.	Command Prompt	Command	Note.
1	C:\>	D:	
2	D:\>	cd ccr	“Space” delimiter is required between “cd” and “ccr”.
3	D:\ccr>	ccrxxxxx /np	“Space” delimiter is required between “xxxxxx” and “/”. “xxxxxx” is different in version.

4-4) If the message “Sensor not connected” appears at starting of the CXDI application, click [OK] button, Change to the “Debugging mode” with the keys ([Alt] + [Tab]) using.

4-5) When Welcome to CCR appears, select “1. Set-Up...”.

2. Installation Manual

- 4-6) When Setting Mode (0: Normal, 1: Expert) [0=0x0]: appears, select "0: Normal."
- 4-7) When CCR SETUP MENU appears, select "7 Scan Sensor Setup".
- 4-8) When Capture Device Configuration Table appears, enter the number of sensor to which make the "Max Capture Device" recognized.
- 4-9) The dummies of "A/D Board Serial Number" are appeared: Enter the sensor serial number for necessary type.

-----A/D Board Serial Number 0 0 -> 11 : 0x199
 -----A/D Board Serial Number 0-1 -> 22 : 0x2009
 -----A/D Board Serial Number 0-2 -> 22 : 0x123
 -----A/D Board Serial Number 0-3 -> 31 : 0x124

For example, when the upright stand model is connected to Sensor 1, and the table model is connected to Sensor 2:

Enter "0000199" for "A/D Board Serial Number for Sensor ID#1"

Enter "00002009" for "A/D Board Serial Number for Sensor ID#2"

The CXDI application can now be launched on the control PC with the same conditions in effect as if an imaging unit were connected.

@@@@@ Capture Device Configuration Table @@@@@

Max Capture Devices [4 = 0x4] : 4 ←Number of imaging units connected

@@@@@ Capture Device Configuration No.0 (SensorID#1 OPU)@@@@@

-----A/D Board Serial Number 0-0 -> 11 : 0x199
 -----A/D Board Serial Number 0-1 -> 22 : 0x2009
 -----A/D Board Serial Number 0-2 -> 22 : 0x123
 -----A/D Board Serial Number 0-3 -> 31 : 0x124

Dummy Serial No. for
Sensor 1

A/D Board Serial Number for SensorID#1 [0x199 = 409] : _____

Custom Type[0:NO CUSTOM 1:STAND 2:TABLE 3:UNIV 4:CASSETTE] [0 = 0x0] : 0

Field of View Rotation (0:No 1:Yes) [0= 0x0] : 0

@@@@@ Capture Device Configuration No.1 (SensorID#2 OPU)@@@@@

-----A/D Board Serial Number 0-0 -> 11 : 0x199
 -----A/D Board Serial Number 0-1 -> 22 : 0x2009
 -----A/D Board Serial Number 0-2 -> 22 : 0x123
 -----A/D Board Serial Number 0-3 -> 31 : 0x124

Dummy Serial No. for
Sensor 2

A/D Board Serial Number for SensorID#2 [0x2009 = 8201] _____

Custom Type[0:NO CUSTOM 1:STAND 2:TABLE 3:UNIV 4:CASSETTE] [0 = 0x0] : 0

Field of View Rotation (0:No 1:Yes) [0= 0x0] : 0

@@@@@ Capture Device Configuration No.2 (SensorID#3 OPU)@@@@@

-----A/D Board Serial Number 0-0 -> 11 : 0x199
 -----A/D Board Serial Number 0-1 -> 22 : 0x2009
 -----A/D Board Serial Number 0-2 -> 22 : 0x123
 -----A/D Board Serial Number 0-3 -> 31 : 0x124

Dummy Serial No. for
Sensor 3

A/D Board Serial Number for SensorID#2 [0x2009 = 8201] _____

Custom Type[0:NO CUSTOM 1:STAND 2:TABLE 3:UNIV 4:CASSETTE] [0 = 0x0] : 0

Field of View Rotation (0:No 1:Yes) [0= 0x0] : 0

@@@@@ Capture Device Configuration No.3 (SensorID#4 OPU)@@@@@

-----A/D Board Serial Number 0-0 -> 11 : 0x199
 -----A/D Board Serial Number 0-1 -> 22 : 0x2009
 -----A/D Board Serial Number 0-2 -> 22 : 0x123
 -----A/D Board Serial Number 0-3 -> 31 : 0x124

Dummy Serial No. for
Sensor 4

A/D Board Serial Number for SensorID#2 [0x2009 = 8201] _____

Custom Type[0:NO CUSTOM 1:STAND 2:TABLE 3:UNIV 4:CASSETTE] [0 = 0x0] : 0

Field of View Rotation (0:No 1:Yes) [0= 0x0] : 0

-----Need to re-start program to validate this change.

2. Installation Manual

- 4-10) When CCR SETUP MENU appears, press the [Esc] key to return to Welcome to CCR.
- 4-11) Select the command "8 - Exit" in the "Welcome to CCR" menu to exit the CXDI application.
- 4-12) After exit the CXDI application and Windows XP desktop appears, starts the command prompt screen (Start ⇒ Program ⇒ Command Prompt). And type the command "ccrxxxxx /np" to start the CXDI application again.
- When the CXDI application program is starting up, the message "There is no BodyPart for SensorID#*. ** TYPE BodyPart will be created" appears. Click [OK]. (* differs according to the type of the sensor.)
→ The above message appears when a /np mode is used with a setting different to that of the connected sensor.
 - The messages "Conflicting X-ray parameters. Do you wish to reset parameters?" and "Conflicting X-ray tube parameters for each imaging method. Do you wish to reset parameters" appear. Click [OK] for each.
→ These above messages might be appeared if /np mode is used with a different setting.
- 5) Going out of /np mode
- Connect the sensor unit to the control PC.
- Before using the system in normal condition, perform the following steps:
- 5-1) If /np mode has been used with a different setting as that of the connected sensor, as mentioned in "(3) Notes", delete the BodyPart**.ini file made in the BodyParts folder, and return the BodyPart**.ini file which has been moved into the BodyParts folder.
- 5-2) Enter the command "ccrstart.bat" on command prompt to boot the CXDI application.
- Follow the procedure from 3) to 9) in previous section. And check these one will be preformed properly without any problems.
- 5-3) Register the ccrstart.bat file to the StartUp.

5.7 Image Quality

(1) Purpose

This procedure is used to check the final image quality of the CXDI.


1) Resolution check

Tools used

(1) Phantom

(2) High-resolution monitor or DICOM printer

Procedure

Procedure/Item	Operation/Conditions
<div style="border: 1px solid black; border-radius: 10px; padding: 10px; text-align: center;"> <p>[Positioning]</p> <p>Position the X-ray tube and CXDI Sensor Unit</p> </div> <div style="text-align: center; margin-top: 20px;">↓</div> <div style="border: 1px solid black; border-radius: 10px; padding: 10px; text-align: center; margin-top: 20px;"> <p>Calibration</p> </div> <div style="text-align: center; margin-top: 20px;">↓</div> <div style="border: 1px solid black; border-radius: 10px; padding: 10px; text-align: center; margin-top: 20px;"> <p>Self-test</p> </div> <div style="text-align: center; margin-top: 20px;">↓</div>	<p>1. Adjust the distance between the focal point of the X-ray tube and the CXDI sensor unit. X cm: Differs according to the grid being used.</p>  <p>2. Perform calibration SYSTEM > CALIBRATION</p> <p>3. Perform self-test. SYSTEM > SELF TEST Must pass all the tests.</p>

2. Installation Manual

Procedure/Item	Operation/Conditions
<pre> graph TD A[Exposure] --> B[Out the image] B --> C[High-resolution monitor] B --> D[DICOM printer] C --> E[Check image quality] D --> E </pre>	<p>4. Irradiate X-ray and capture the image of a phantom.</p> <p>5. Output the image to a high-resolution monitor or DICOM printer.</p> <p>6. Set the high-resolution monitor and DICOM printer by referring to their instruction manuals.</p> <p>7. Check that there is no artifacts, shading, grid stripes, etc. on the image.</p>

2. Installation Manual

5.8 Post-installation checks

1) Check sheet

Checkpoint	Checkpoint details	Check
Checking the imaging unit	Align the unit with the X-ray tube	<input type="checkbox"/>
	Check that the unit does not interfere with the cables.	<input type="checkbox"/>
Checking the date and time	Set the date.	<input type="checkbox"/>
	Set the time.	<input type="checkbox"/>
	Set the time zone.	<input type="checkbox"/>
Checking the software version	Check that the CXDI application, firmware and PLD code versions all match.	<input type="checkbox"/>
Identifying and registering the imaging units	Register the serial numbers of the sensors	<input type="checkbox"/>
Inputting the control PC serial number	Input the serial number of the control PC to be used.	<input type="checkbox"/>
Checking the operation unit	Set the contrast.	<input type="checkbox"/>
	Set the brightness.	<input type="checkbox"/>
	Set the gamma correction.	<input type="checkbox"/>
Checking the exposure condition table	kV	<input type="checkbox"/>
	mA	<input type="checkbox"/>
	msec or mAs	<input type="checkbox"/>
Checking the annotation	Check that the setting have been made in accordance with the customer's request.	<input type="checkbox"/>
Network connections	IP address	<input type="checkbox"/>
	Subnet mask	<input type="checkbox"/>
	Default gateway	<input type="checkbox"/>
Preparations prior to exposure	Perform calibration.	<input type="checkbox"/>
	Perform self-test.	<input type="checkbox"/>
Checking image transfer to printers and storages	Check that the setting have been made in accordance with the customer's request.	<input type="checkbox"/>
Checking image transfer to external memory device	Check that the image is transferred properly.	<input type="checkbox"/>
Checking the image quality	Use SMPTE pattern to check the density on a linear chart.	<input type="checkbox"/>
	Check that there is no artifacts, shading, etc.	
Deleting unnecessary data (there must be no unnecessary data such as the images used for testing)	dtque	<input type="checkbox"/>
	dtstore	<input type="checkbox"/>
	dttmp	<input type="checkbox"/>
	old	<input type="checkbox"/>
	Windows XP trash box	<input type="checkbox"/>
Checking the window displays (no unnecessary windows must appear; the same applies after rebooting)	Operate from the Windows XP desktop.	<input type="checkbox"/>
	Taskbar	<input type="checkbox"/>


2. Installation Manual

Checkpoint	Checkpoint details	Check
Inserting the backup floppy disk and checking the backup files	Create the backup files in floppy drive by re-starting. (Cannot be used in automobile)	<input type="checkbox"/>
Backing up ccr folder	D:ccr	<input type="checkbox"/>
Registering in startup. (Check by rebooting)	Check that the CXDI application starts.	<input type="checkbox"/>
	Check that no /d, /np or other flags have been raised.	<input type="checkbox"/>
Communication with X-ray generators	kV, mA, msec, body part settings, etc.	<input type="checkbox"/>

[Table.1]

6 Dimension

(1) Imaging Unit




Unit: mm

Mass: 4.8 Kg (except the cable)
5.7 Kg (with 7m cable)
5.2 Kg (with 3m cable)

2. Installation Manual

(2) Power Box




Unit: mm

Mass: 4.2Kg

2. Installation Manual


(3) Remote Switch



Unit: mm

Mass: 0.5Kg

(4) Grid (Optional)



Unit: mm

Mass: 0.9Kg (Frame)


CXDI-50G

3. Function

Content

1	Imaging Unit.....	1
1.1	PCB-50Di board.....	2
1.2	PCB-50 LED board.....	2
2	Power Box	3
2.1	PCB-50 X-ray board	3
2.2	Remote switch.....	3
2.3	50 Power supply	4
3	Available Imaging Time (Normal Imaging/Long-term Imaging)	5
4	About the Power Box Initialization Switch.....	8
5	How to Access to OS.....	9

1 Imaging Unit



The Imaging Unit's function is listed below:

- (1) Converts the acquired X-ray image to light signal using the fluorescent screen and stores.
- (2) After reading the stored electric signal (Image) from the sensor, perform the A/D conversion and stores it on the frame memory temporally.
- (3) Reduce the electric signal at the same time as storing and transfer it to the Control PC through the Power Box.

3. Function

1.1 PCB-50Di board

The PCB-50Di board has the following functions:


- (1)The sensor driving control. Reading the digital image signals outputted from the AD converter (PCB-50AD)
- (2)The communication, the X-ray image transferring with the Control PC through the Power Box on the Ethernet.
- (3)The synchronization between the X-ray generator and the image acquisition through the Power Box.
- (4)The control of the LED displaying.
- (5)Detecting the Grid by using the Grid detecting sensor.
- (6)Relaying the power which Power Box supplies to the PCB-50AD.
- (7)Detecting the unusual temperature, error reporting and stop the Sensor driving.
- (8)Detecting the X-ray emission status.
- (9)Holding the data factory set.

1.2 PCB-50 LED board

The PCB-50 LED board has the following functions.

- (1)Power supply relaying (5.5V/3.3V/24V/-10V)
- (2)LED control (POWER/READY/BUSY)
- (3)The detecting Grid sensor connection.
- (4)The case grounding around power supply.
(Each power supply cable must be put on the case grounding point with the screws.)

2 Power Box



The Power Box consists of the following parts; 50PCB-XRAY board (X-ray I/F), Power supply, Remote power switch. And it has the function that is the signal transition with Imaging Unit, Power supplying, the signal transition with the X-ray generator. The Power Box can be connected only one Imaging Unit.

2.1 PCB-50 X-ray board

The PCB-50 X-ray board has the following function.

- (1) The Interface with the X-ray generator.
- (2) Relaying the signals insulating the Internet transition. (AC230V Basic Insulation)
- (3) The cable length setting (3/7m) in the 50 Power supply capacity.
- (4) The firm initializing code on the Imaging Unit boot switch is installed.

2.2 Remote switch

- (1) Output control of the 2nd side on the 50 Power supply (7m) or 50 Power supply (3m)

3. Function

2.3 50 Power supply

(1) ACDC power supply Imaging Unit mainly use

Rated power supply (input) : AC 100 to 120V/AC 200 to 240V

Rated power supply (output) : CH1 9.5V, CH2 9.5V, CH3 6.8V, CH4 -11.5V, CH5 27V

(2) Added function

a) Over current protection: At detecting the over current, shutdown and reset is performed automatically

CH1, 2: Automatic current limiting over 105% of the PEAK Current (3.5A)

CH3: Shutdown over 200% of the NOMINAL Current (2.5A)

CH4: Automatic current limiting over 105% of the NOMINAL Current (0.2A)

CH5: Automatic current limiting at the Load Current (500mA)

* When the CH3 is shutdown, CH4 and CH5 is shutdown at the same time.

b) Over Voltage protection: When detecting the over voltage, shutdown the output.

Over 115% of the rated voltage

C) The switching (ON/OFF) of the 2nd side output voltage by using the remote ON/OFF controller is available

2nd side output display: LED (Green)

3. Function

3 Available Imaging Time (Normal Imaging/Long-term Imaging)

[Overview]

There are two available imaging times as follow:

- 1) Normal imaging (0 - 1000 msec)
- 2) Long-term imaging (1001 - 3000 msec)

From Version 6.0, the maximum imaging time is now 3 seconds for the CXDI-50G sensor, which can be set on the GUI.

[Precaution]

- The preview display becomes slower when using long-term imaging.
- The preview display may also become slower ^{*1} when performing normal imaging using the part button that is set to long-term imaging (imaging time settings: 1001 msec to 3000 msec).
^{*1} The preview display becomes slower without the X-ray monitor, that is, when using the CXDI-50G.
(When an X-ray exposure negative cannot be detected, even if the X-ray monitor is used.)
- Imaging preparation time: 10 seconds for normal imaging and 30 seconds for long-term imaging. In imaging preparation time, the imaging unit changes from sleep status (sensor in standby status) to ready status (possible to perform imaging).
(The imaging cycle time ^{*2} becomes longer.)

^{*2} Time required preparing for the next imaging after a single imaging is done. Normal imaging: 15 sec, long-term imaging: 30 sec.

[Technical Description]

1. The maximum value for imaging condition

- When using the CXDI-50G sensor, the maximum value of the exposure time is 3000 msec, which can be set on the screen.
- The maximum value of the tube current is 1600 mA. - The maximum mAs value is 4800mAs due to the maximum value of the exposure time changing to 3000.

The maximum value of the tube current is 1600mA. The maximum value of the mAs value is changed from the 3000 maximum value of the exposure time to 4800 mAs.

	Exposure time	Tube current	mAs value
Up to CXDI V5.1	1000msec ↓	5000mA ↓	5000mAs ↓
CXDI-11- CXDI-31 sensor	1000msec	1600mA	1600mAs
CXDI-40G or later version sensor	3000msec	1600mA	4800mAs

Table 3-1

2. Imaging condition check at the time of upgrade

If any of the kV, mA, mAs, cm (except msec) values recorded in the imaging condition table or in each body part information exceeds the limit of the sensor, when the CXDI starts up, a warning message will be displayed (Fig. 1) and the value will be automatically modified to be at or below the limit. (However, thinking from the range of values that can

3. Function

be used with the generator, the probability of the warning message is very low.)




Figure 3-1

3. Adding values to the imaging conditions table

It is possible to add values up to 3000 msec, 4800 mAs to the imaging conditions table. However, at the time of the actual imaging, if the exposure is performed with a CXDI-11 - CXDI-31 sensor, it is not possible to set values higher than 1000 msec, 1600 mAs.

4. Imaging conditions table

It is possible to add values up to 3000 msec and 4800 mAs to the system settings - imaging conditions table on the settings screen. However, if 1001 - 3000msec, 1601 - 4800mAs values are added, a warning message will be displayed only once, saying the values cannot be used with the CXDI-11 - CXDI-31 sensors. [Figure 3-2]

If at the time of a regular exposure or a calibration exposure, the imaging body part of a CXDI-11 - CXDI-31 sensor was selected, values higher than 1000 msec, 1600 mAs cannot be selected from the imaging conditions table.




Figure 3-2

3. Function

5. msec maximum value checking

Even if the values recorded in the msec values of calibration/imaging body part within the BodyPart.ini exceed the maximum msec value of the sensor, the OPU can perform the exposure using those values without checking. (This function was already implemented before CXDI v5.1.)

It is the same when using the msec imaging conditions table, if a value bigger than the sensor's maximum msec value is written in the BodyPart.ini file, the value will not be automatically replaced with the value of the imaging conditions table, but can be used for the exposure as it is.

Note:

In the case of mAs lead, the msec will be automatically recalculated based on the mA, mAs, and the msec value will be automatically overwritten.

6. kV, mA, mAs, cm maximum value check

If any of the kV, mA, mAs, cm values of the calibration/imaging body part recorded within the BodyPart.ini file exceeds the maximum value of the sensor, when the CXDI starts up, a warning message will be displayed and the value will be automatically modified to be at or below the limit. (If the imaging conditions table is used, a table value not exceeding the maximum value of the sensor will be specified.)

3. Function

4 About the Power Box Initialization Switch

Initialization Switch

The LAN can be started with the factory settings when you turn on the power (the main power of the power box and remote switch) by holding down the initialization switch (see figure ^{*1}) of the power box.

The 50G firmware contains the initialization and normal codes.

(They are stored in the PCB-50Di flash ROM)

Normally, the normal code runs on a steady basis, and only normal code is updated when upgrading the firmware.

Use the initialization code when the normal code cannot start for some reason or when you have lost the Ethernet settings. Using the initialization code sets the Ethernet-related settings to the default settings and allows you to perform the startup operation for the initialization code.

In this case, the connection can be made by setting the Ethernet settings in the control PC to the 50G default^{*2}.

This default connection allows you to upgrade the firmware again and also check and set the Ethernet settings again in order to recover the system.



^{*1} Initialization Switch: Switch 1 mounted on PCB-50 XRY

^{*2} Default settings: IP Address=192.168.100.11 (**factory setting**)

5 How to Access to OS

This is the procedure for shutting down the CXDI system and accessing to Windows.

1.1 Preparation


Prepare a keyboard and mouse.

1.2 Notes

- (1) Never perform the following operation when the CXDI host program is operating, such as during QA process, image transfer, communication with RIS or generator, etc.
- (2) Access to the OS is allowed only by the service engineer. Since important settings and files are saved, never let the user access the OS because CXDI system will not operate normally if the operation is not performed properly.

1.3 Procedures

- (1) Turn ON the power of the control PC.
- (2) When the exposure screen of the CXDI appears, press [Alt] and [Tab] keys on the keyboard together.
- (3) Keep [Alt] key pressed even after the display as shown below appears. Press [Tab] key while pressing [Alt] key to select the command prompt window.



- (4) CCr Console Menu will appear. Press [Esc] key. [***** Welcome to CCR *****] will appear. Enter 8 after “Enter item:” and press [Enter] key.

```
***** Welcome to CCR *****
1 Set-Up...          5 -
2 Display Set-Up    6 -Utilities...
3 Image Util...     7 - Exit
Enter item: 8
```

- (5) A message prompting you to press a key will appear. Press any key. CCR start software will shut down.
- (6) Desktop screen of Windows XP will appear.

CXDI-50G


4. Repair Guide

Content

1	Disassemble/Reassemble.....	1
1.1	Removing Grip unit	1
1.2	Removing the side cover	2
1.3	Removing the cover	3
1.4	Exchanging the sensor cable	4
1.5	Removing the PCB-50 LED	5
1.6	Attaching the PCB-50Di	6
1.7	Attaching the PCB-50AD	7
1.8	Attaching the PCB-50XRAY	8
2	PCB Settings.....	9
3	Operation Required for Replacing Parts.....	12

4. Repair Guide

1.2 Removing the side cover



1. Loosen the screw (x2x2) fix the side cover (L_ASM) and (R_ASM). And remove the cover carefully because the cover is pushed into the ditch so as not to come out.
2. Lift the side cover (C_ASM) with a little and remove it.
3. Applied the solvent, loosen the screw (x2) and remove the plate.


Exchange the shock sensor when its color is red.

Note:

1. Handle with carefully so that the defect should not adhere.

4. Repair Guide

1.3 Removing the cover




1. Remove the sleeve cover (x11).
2. Remove the screw (M3x8) or screw (M3x12).
3. Remove the insulation sleeve and base cover.

Note:

1. Handle with care so that the defect should not adhere.
2. The insulation sleeve and sleeve cover must not be lost.
3. The order of detaching the screws fixes the base cover is not asked especially. At assembling, check the screw length, tight the screws evenly and be careful not to tighten it so much.

4. Repair Guide

1.4 Exchanging the sensor cable




1. Remove the screw (M3x10 x2) fixes the cable clamp1.
2. Remove the screw (M3x6 x2) fixes the plate.
3. Remove the screw (M3x6 x2) fixes the cable clamp2. Do not lose the screw because it is held by the clamp cushion.
4. Remove the each connector with which PCB-40 LED and PCB-50Di.
5. Remove the 50G sensor cable unit.

Note:

1. At the assembling, drawing the cable carefully so as not to crowd.
2. Adjust the bush so that the 50G sensor cable unit line may become straight and set the bush to the installation position.

4. Repair Guide

1.5 Removing the PCB-50 LED




1. After removing the connector connected with the PCB-50LED unit, loosen the screw (x2) fixes the Grid detect sensor on the top cover and remove this screw.
2. Loosen the screw (x4) fixes the PCB-50 LED on the top cover and remove this PCB.

Note:

1. At the assembling, draw the cable carefully so as not to crowd.
2. Do not tighten the screw so much.

4. Repair Guide

1.6 Attaching the PCB-50Di




1. Remove the flat cable.
2. Loosen the screw (M2.6 x 12) fixes the PCB-50Di and remove it.

Note:

1. **At assembling, insert the connector carefully in the direction of the flat cable.**
2. **At assembling, there must not be a foreign body on the spacer sheet.**
3. **Exchange the flat cable for parts with a new one used one.**

4. Repair Guide

1.7 Attaching the PCB-50AD





1. Remove the flat cable.
2. Loosen the screw (M2.6 x 16) fixes the PCB-50AD and remove it.

Note:

1. At assembling, insert the connector carefully in the direction of the flat cable.
2. Exchange the flat cable for parts with a new one used one.

4. Repair Guide

1.8 Attaching the PCB-50XRAY



1. Remove the connector of each cable.
 - (1) Sensor cable (J002/CN2)
 - (2) X-ray I/F cable (J004)
 - (3) Remote switch cable (CN4)
 - (4) PCB-50XRAY board/50 Power supply (J001/CN3)
2. Loosen the screw fixes the PCB-50XRAY and remove it.

Note:


1. The power supply cable must be removed before assembling.

4. Repair Guide

2 PCB Settings

(1) Sensor Unit

1) PCB-50Di (BG7-2766)



<SW1>

SW1		Function
1	OFF	Not used.
2	OFF	Starts the Initialize code by force ON: Yes OFF: No
3	OFF	SW1-2 ON Ether Setting FlashROM Read ON: Yes OFF: No
4	OFF	Not used.
5	OFF	Not used.
6	OFF	Not used.
7	OFF	Detects cable length automatically. ON: Disable OFF: Enable
8	OFF	SW1-7 ON ON:3m OFF:7m

4. Repair Guide

<SW2>

SW2		Function
1	OFF	Sub No. by Product type “1” It changes when PCB is changed, etc.
2	OFF	
3	OFF	
4	OFF	
5	OFF	Product type “7” “7” indicates CXDI-50G.
6	OFF	
7	OFF	
8	ON	

<SW4>

SW4		Function
1	OFF	LANC I/O address
2	OFF	
3	OFF	
4	ON	EEPROM ON: Disable OFF: Enable
5	OFF	Not used.
6	OFF	H-UHI ON: Use OFF: No use

2) PCB-50LED (BG7-2767)


No special setting.

3) PCB-50AD (BG7-9061)

No special setting.

4. Repair Guide

(2) Power Box



1) PCB-50XRAY (BG7-2770)

<JP1>

Short the JP1 according to the power unit.

JP1	Function
6-8 Short	50 Power Unit 7m (BG7-2857)
7-8 Short	50 Power Unit 3m (BG7-2858)


How to discriminate between the power boxes:

50 Power Unit 7m

	1	2
Alphabet on the label	A	A
Color of the label	--	White

50 Power Unit 3m

	1	2
Alphabet on the label	B	B
Color of the label	--	Pink



3 Operation Required for Replacing Parts

Perform the following operations when the unit is replaced.

3.1 Sensor unit

(1) When sensor unit is replaced

1) Set the IP address. (This operation is not required if the default IP address is used.)

Refer to “Imaging unit IP address setting” in the Tool Software Operation Manual for CXDI-50G.

2) Check the version of firmware and PLD code version.

Refer to “(2) Checking the Firmware Version” in “5.2.5 Settings” in “2.5 Installation” of “2. Installation Manual”.

3) Install the firmware and PLD code as required.

Refer to “(3) Installing Firmware and PLD Code” in “5.2.5 Settings” in “2.5 Installation” of “2. Installation Manual”.

4) Identify the sensor unit.

Refer to “(6) Identifying the Sensor Units” in “5.2.5 Settings” in “2.5 Installation” of “2. Installation Manual”.

5) Change total number of exposures. (Basically the counter should be reset to “0” when the sensor unit is replaced.)

Refer to “(13) Changing the Total Image Count” in “5.2.5 Settings” in “2.5 Installation” of “2. Installation Manual”.

6) Check the image quality.

Refer to “5.2.6 Image Quality” in “2.5 Installation” of “2. Installation Manual”.

7) Back up the data. (Back up the data to FD as required.)

Refer to “Backing Up when Installing” and “(15) Backing Up Setting Data to FD” in “5.2.5 Settings” in “2.5 Installation” of “2. Installation Manual”.

(2) When PCB-50Di (BG7-2766) is replaced

1) Set the PCB dipswitches.

Refer to “2.1 PCB-50Di” in “2. Settings” of “4. Repair Guide”.

2) Set the IP address. (This operation is not required if the default IP address is used.)

Refer to “Imaging unit IP address setting” in the Tool Software Operation Manual for CXDI-50G.

2) Check the version of firmware and PLD code version.

Refer to “(2) Checking the Firmware Version” in “5.2.5 Settings” in “2.5 Installation” of “2. Installation Manual”.

3) Install the firmware and PLD code as required.

Refer to “(3) Installing Firmware and PLD Code” in “5.2.5 Settings” in “2.5 Installation” of “2. Installation Manual”.

4. Repair Guide

4) Install the sensor serial number.

Refer to “(4) Checking the Sensor Serial Number” in “5.2.5 Settings” in “2.5 Installation” of “2. Installation Manual”.

5) Install the sensor data file.

Refer to “DP File Write Tool Software” in the Tool Software Operation Manual for CXDI-50G.

To perform this operation, “Sensor Data File FD” that comes with the sensor unit is required.

6) Check the image quality.

Refer to “5.2.6 Image Quality” in “5.2.5 Settings” in “2.5 Installation” of “2. Installation Manual”.

(3) When PCB-50LED (BG7-2767) is replaced

1) Check that the LED lights.

2) Check the image quality.

Refer to “5.2.6 Image Quality” in “5.2.5 Settings” in “2.5 Installation” of “2. Installation Manual”.

(4) When PCB-50AD (BG7-2770) is replaced

1) Check the image quality.

Refer to “5.2.6 Image Quality” in “5.2.5 Settings” in “2.5 Installation” of “2. Installation Manual”.

3.2 Power box

(1) When PCB-50XRAY (BG7-2770) is replaced

1) Set the jumper pins on the PCB.

Refer to “(2) Power Box” in “2 PCB settings” in “4. Repair Guide”.

2) Check that the system starts up normally and that operations such as exposure, images capture and data transfer are performed normally.

(2) When 50 Power Unit 7m (BG7-2857) / 3m (BG7-2858) is replaced

1) Check that the system starts up normally and that operations such as exposure, images capture and data transfer are performed normally.

CXDI-50G

5. Parts Catalog

CONTENTS

CXDI-50G..... 1

IMAGING UNIT 2

POWER BOX 3





REMOTE SWITCH UNIT 4








IMAGING UNIT (Electrical) 5

POWER BOX (Electrical) 6


INDEX OF PARTS NUMBERS 7

Key NO.	Description	Part No.	Q'ty
1.....	IMAGING UNIT		1
2.....	POWER BOX (7m)	Y67-2669-000	1
	POWER BOX (3m).....	Y67-2670-000	1
3.....	CABLE UNIT, X-RAY I/F	BG7-2855-000	1
4.....	SWITCH UNIT, REMOTE	BG7-2772-000	1
5.....	CABLE UNIT, POWER, 100V	BG7-2145-000	1
6.....	CABLE UNIT, POWER, 120V	BG7-2309-000	1
7.....	CABLE UNIT, POWER, 230V	BG7-2310-000	1
8.....	HOLDER, AC POWER CABLE.....	BA4-1805-000	1
9.....	SCREW	XB1-2300-406	2
10.....	CLAMP, CABLE.....	WT2-5859-020	1
11.....	SCREW	XB1-2400-606	1


Key No.1	Key No.2
	
Key No.3	Key No.4
	

Key No.5	Key No.6
	
Key No.7	Key No.8
	
Key No.9	Key No.10
	
Key No.11	
	


KEY NO.	PARTS NO.	Q'TY	DESCRIPTION	MEMO
1	Y67-2671-000	1	COVER UNIT, BASE	
2	BF0-5418-010	1	COVER, SIDE (R_ASM)	
3	BF0-5417-010	1	COVER, SIDE (L_ASM)	
4	BF0-5419-010	1	COVER, SIDE (C_ASM)	
5	BA4-1783-000	4	SCREW	
6	XB1-2301-206	5	SCREW	
7	BG7-2761-000	1	CABLE UNIT, 7M	
	BG7-2782-000	1	CABLE UNIT, 3M	






KEY NO.	PARTS NO.	Q'TY	DESCRIPTION	MEMO
1	XB1-2300-806	15	SCREW	
2	XB1-2300-806	11	SCREW	
3	BA4-1775-000	11	SLEEVE, ISOLATION	
4	BA4-1776-000	11	CAP, SLEEVE	
5	BA4-1789-000	4	SENSOR, SHOCK	
6	XB1-2260-606	8	SCREW	





KEY NO.	PARTS NO.	Q'TY	DESCRIPTION	MEMO
1	BG7-2766-000	1	PCB UNIT, DIGITAL	
2	BG7-2767-000	1	PCB UNIT, LED	
3	BG7-9061-000	2	PCB UNIT, A/D	
4	BF0-5372-020	1	CLAMP UNIT	
5	BH6-5700-000	2	CABLE, FLAT	
6	BH6-5701-000	2	CABLE, FLAT	
7	BH6-5719-000	4	CABLE, FLAT	
8	BH6-5720-000	1	CABLE, FLAT	
9	BH6-5721-000	1	CABLE, FLAT	
10	BH6-5722-000	1	CABLE, FLAT	
11	BH6-5723-000	2	CABLE, FLAT	
12	BH6-5724-000	1	CABLE, FLAT	
13	XB1-2260-606	16	SCREW	
14	XB1-2260-606	12	SCREW	
15	XB1-2260-606	8	SCREW	
16	BG7-2768-000	1	SWITCH UNIT, GRID	
17	XA1-1200-506	2	SCREW	
18	BA4-1787-020	1	CLAMP, CABLE	
19	BA4-1788-000	1	PLATE, CABLE	
20	XB1-2301-006	2	SCREW	
21	XB1-2260-606	2	SCREW	
22	XB1-2260-606	4	SCREW	





KEY NO.	PARTS NO.	Q'TY	DESCRIPTION	MEMO
1	BA4-1792-000	1	HADLE, IMAGING UNIT	
2	BA4-1793-000	2	CAP, HANDLE	
3	BA4-1794-000	2	PLATE, HANDLE	
4	XB6-7401-209	2	SCREW	

Key No.1	Key No.2
	
Key No.3	Key No.4
	


KEY NO.	PARTS NO.	Q'TY	DESCRIPTION	MEMO
1	XB1-2300-406	3	SCREW	
2	XB1-2300-806	4	SCREW	
3	BA4-1803-000	4	PAD	
4	XB1-2300-406	8	SCREW	
5	BA4-1800-020	1	UPPER COVER, POWER BOX	
6	XB2-7300-606	5	SCREW, W/WASHER	
7	XB1-2300-406	2	SCREW	
8	XB1-2300-406	2	SCREW	
9	BA4-1802-000	1	COVER, CABLE	




KEY NO.	PARTS NO.	Q'TY	DESCRIPTION	MEMO
1	BG7-2770-000	1	PCB UNIT,X-RAY I/F	
2	BG7-2856-030	1	CABLE UNIT, POWER SUPPLY	
3	BG7-2857-000	1	POWER SUPPLY UNIT, 7M	
	BG7-2858-000	1	POWER SUPPLY UNIT, 3M	
4	WB2-5019-000	1	RELAY, DC	
5	WS1-0287-000	1	PLUG, 2P	




KEY NO.	PARTS NO.	Q'TY	DESCRIPTION	MEMO
1	Y67-2659-000	1	SWITCH, LOCKER	
2	XZ9-0488-000	2	MAGNET CATCH	



SYMBOL	PART NO.	DESCRIPTION	REMARKS
CA1	BG7-2761-000	CABLE UNIT, 7M	
	BG7-2782-000	CABLE UNIT, 3M	
CA2	BH6-5719-000	CABLE, FLAT	
CA3	BH6-5700-000	CABLE, FLAT	
CA4	BH6-5701-000	CABLE, FLAT	
CA5	BH6-5723-000	CABLE, FLAT	
CA6	BH6-5721-000	CABLE, FLAT	
CA7	BH6-5719-000	CABLE, FLAT	
CA8	BH6-5719-000	CABLE, FLAT	
CA9	BH6-5723-000	CABLE, FLAT	
CA10	BH6-5722-000	CABLE, FLAT	
CA11	BH6-5700-000	CABLE, FLAT	
CA12	BH6-5701-000	CABLE, FLAT	
CA13	BH6-5719-000	CABLE, FLAT	
CA14	BH6-5724-000	CABLE, FLAT	
CA15	BH6-5720-000	CABLE, FLAT	
SW1	BG7-2768-000	SWITCH UNIT, GRID W/CABLE	
PB1	BG7-2766-000	PCB UNIT, DIGITAL	
PB2, 3	BG7-9061-000	PCB UNIT, A/D	
PB4	BG7-2767-000	PCB UNIT, LED	



SYMBOL	PART NO.	DESCRIPTION	REMARKS
CA1	BG7-2145-000	CABLE UNIT, POWER, 100V	
	BG7-2309-000	CABLE UNIT, POWER, 120V	
	BG7-2310-000	CABLE UNIT, POWER, 230V	
CA2	BG7-2856-030	CABLE UNIT, POWER SUPPLY	
CA3	BG7-2855-000	CABLE UNIT, X-RAY I/F	
CA4	BG7-2761-000	CABLE UNIT, 7M	
	BG7-2782-000	CABLE UNIT, 3M	
SW1	BG7-2772-000	SWITCH UNIT, REMOTE	
PB1	BG7-2770-000	PCB UNIT,X-RAY I/F	



INDEX OF PARTS NUMBERS

PARTS NO.	PAGE	REVISION NO. - REPORT NO.				
BA4-1775-020	2-2	-	-	-	-	-
BA4-1776-020	2-2	-	-	-	-	-
BA4-1783-000	2-1	-	-	-	-	-
BF0-5417-010	2-1	-	-	-	-	-
BF0-5418-010	2-1	-	-	-	-	-
BF0-5419-010	2-1	-	-	-	-	-
BA4-1787-020	2-3	-	-	-	-	-
BA4-1788-000	2-3	-	-	-	-	-
BA4-1789-020	2-2	-	-	-	-	-
BA4-1792-000	2-5	-	-	-	-	-
BA4-1793-000	2-5	-	-	-	-	-
BA4-1794-020	2-5	-	-	-	-	-
BA4-1800-020	3-1	-	-	-	-	-
BA4-1802-000	3-1	-	-	-	-	-
BA4-1803-000	3-1	-	-	-	-	-
BA4-1805-000	1-1	-	-	-	-	-
BF0-5372-020	2-3	-	-	-	-	-
BG7-2145-000	1-1	-	-	-	-	-
BG7-2309-000	1-1	-	-	-	-	-
BG7-2310-000	1-1	-	-	-	-	-
BG7-2761-000	2-1	-	-	-	-	-
BG7-2766-000	2-3	-	-	-	-	-
BG7-2767-000	2-3	-	-	-	-	-
BG7-2768-000	2-3	-	-	-	-	-
BG7-2770-000	3-2	-	-	-	-	-
BG7-2772-000	1-1	-	-	-	-	-
BG7-2782-000	2-1	-	-	-	-	-
BG7-2855-000	1-1	-	-	-	-	-
BG7-2856-030	3-2	-	-	-	-	-
BG7-2857-000	3-2	-	-	-	-	-
BG7-2858-000	3-2	-	-	-	-	-
BG7-9061-000	2-3	-	-	-	-	-

INDEX OF PARTS NUMBERS

PARTS NO.	PAGE	REVISION NO. - REPORT NO.				
BH6-5700-000	2-3	-	-	-	-	-
BH6-5701-000	2-3	-	-	-	-	-
BH6-5719-000	2-3	-	-	-	-	-
BH6-5720-000	2-3	-	-	-	-	-
BH6-5721-000	2-3	-	-	-	-	-
BH6-5722-000	2-3	-	-	-	-	-
BH6-5723-000	2-3	-	-	-	-	-
BH6-5724-000	2-3	-	-	-	-	-
WB2-5019-000	3-2	-	-	-	-	-
WS1-0287-000	3-2	-	-	-	-	-
WT2-5859-020	1-1	-	-	-	-	-
XA1-1200-506	2-3	-	-	-	-	-
XA1-2260-606	2-2,2-3	-	-	-	-	-
XB1-2300-406	1-1,3-1	-	-	-	-	-
XB1-2300-806	2-2,3-1	-	-	-	-	-
XB1-2301-006	2-3	-	-	-	-	-
XB1-2301-206	2-1	-	-	-	-	-
XB1-2400-606	1-1	-	-	-	-	-
XB2-7300-606	3-1	-	-	-	-	-
XB6-7401-209	2-5	-	-	-	-	-
XZ9-0488-000	4	-	-	-	-	-
Y67-2659-000	4	-	-	-	-	-
Y67-2669-000	1-1	-	-	-	-	-
Y67-2670-000	1-1	-	-	-	-	-
Y67-2671-000	2-1	-	-	-	-	-

CXDI-50G

6. Troubleshooting

Content

1	Gathering Information about Problems	1
2	How to back up and recover the system	3

CXDI V6.00 Error code

1 Gathering Information about Problems

1.1 Outline

It is recommended to replace the whole unit (50G, OPU, power box, C3S) if any problem occurs at the customer's site in order to reduce the downtime of the system.

It is desirable to have the bad unit brought back and repaired. (Although it depends on the kind of the problem.)

This section explains about the information (log file) required to know what has occurred and what to be done.

1.2 Probable problems

- System connection failure and condition setting failure during installation
- Electrical and mechanical system failure, malfunctioning, bad image, noise, and communication error
- Software and specifications problem

1.3 Required information

1.3.1 When Dr. Watson Error occurs

Gather information when:

- Communication error related to Dr. Watson occurred between the OPU and the CXDI, resulting in CXDI application failure
- Display on the OPU freezes and cannot be recovered

(1) Environmental information (such as version of the CXDI host program, composition of hardware and optional software)

(2) Dr. Watson log

C:\Documents and Settings\All Users\Application Data\Microsoft\Drwatson\drwts32.log

(3) Event viewer system log

C:\WINDOWS\system32\config\SysEvent.Evt

(4) The whole D:\Ccr folder

Depending on the timing the error has occurred, images may be saved in a folder before dtstore. In this case, copy dttmp and dtque folder.

1.3.2 When Error occurs

Information required differs according to whether optional module (such as DMW, generator communication module, etc.) is used or not.

(1) Log files and information required no matter optional module is used or not

- 1) How the system is used at the customer's site (System composition)
- 2) Version of CXDI host program
- 3) Error message and code
- 4) All the INI files directly under CCR folder

6. Troubleshooting

5) All the BodyParts folders

All of the above five items are necessary to see how the CXDI is set. If the problem has occurred in the CXDI, the information is required to have the problem occur again.

6) opu3.log and opu3_YYYYMMDDHHMMSS.log

When file size exceeds 1 MB, opu3.log makes a new “opu3.log” with a different name in “opu3_YYYYMMDDHHMMSS.log” when the system is restarted.

Ten history files in the past will be saved.

Because a new log is made when the file size is large, log at the time the error occurred may be in a file other than “opu3.log”.

Since location of the log cannot be checked at the customer's site, please be sure to collect not only the opu3.log but all the history files.

7) syslog

8) Dr. Watson log

9) Event viewer system log

(2) Required log files and information according to the used optional module

Please also gather the following files and information other than those indicated in (1).

(2-1) DMW

1) chmwm.ini

2) ccMax_ws.ini

chmwm.ini/ccMax_ws.ini will be collected automatically when all the INI files directly under CCR folder are collected.

3) chmwm.log

4) DICOM conformance statement of RIS

(2-2) Generator communication module

1) cgbig3.ini

2) StrTable.ini

StrTable.ini will be collected automatically when all the INI files directly under CCR folder are collected.

3) Character string (such as error code) that is displayed in the error dialog box

1.3.3 When image is bad

1) How the system is used at the customer's site (System composition)

2) Version of CXDI host program

3) D:\ccr

4) Bad image and the images taken before and after it

2 How to back up and recover the system

[Objective]

This document describes how to back up and recover the system.

[Technical Description]

There are two system backup methods as follow:

The recovery method required depends on the way the system crashes.

Backup method

- A) Backup using floppy disks
- B) Backup using a hard drive

1. Backup method

- A) Backup method using floppy disks

The network settings configured in each installation site and the customized body part settings are stored in each ini file.

All the ini files are stored on a floppy disk when starting up the control PC.

The system has a feature that stores the latest ini files on the floppy disk at the system startup by updating the ini files with modifications users made while using the system.

- B) Backup method using a hard drive

The control PC has no feature that mirrors all the files including the OS to other hard drives.

Therefore, to be ready for hard drive crashes, we recommend that you add another hard drive when installing the system, in order to copy the software between the hard drives using Ghost or Drive Copy, which are available on the market.

This should be conducted at the final installation stage (just before delivery to users).

As an alternative, you can also provide a hard drive that contains the OS (before activation) and drivers in case of hard drive crashes.

2. Recovery method

2.1 When problems occur in a Ccr software ini file

The system can be recovered to the last environment status just before the system was used by users when problems^{*1} occur in d:\Ccr software other than the OS.

^{*1} When the setting data or files are damaged

In this case,

The recovery can be made by overwriting ini files stored on the floppy disk to d:\ccr.

6. Troubleshooting

2.2 When problems occur in Ccr software

When problems occur in files other than ini files for d: \Ccr software other than the OS, recovery can be accomplished by adding or replacing the relevant files if you can identify the defective files. Recover Ccr with the following procedure if you cannot identify the defective files:

- 1) Copy d: \ccr to a different directory or laptop computer.
- 2) Delete d: \ccr, and then newly install the CXDI software. (Note)
(Note) The same version of the software must be installed.
- 3) Copy the following files in Ccr that were copied in Step 1) to d: \ccr
 - \dtstore (captured images)
 - \Logs
 - \White.dcm
 - \defpix#.dat
 - \xxxxxx.dp
- 4) Newly install the optional software (DMW/Gen.communication) if you are using it.
- 5) Copy to overwrite all the ini files in d: \Ccr stored on the floppy disk in order to recover the user's environment.
- 6) Perform the settings again that are described in the "Control PC serial number" and "Setting the imaging unit identification and the number of connecting units" in this manual "Setting Procedures".

2.3 When the hard drive crashes

Recover the system using the following method when the hard drive crashes.

- 1) Replace the crashed hard drive with the hard drive provided in item B above, "Backup method using a hard drive".

* Copy \Ccr from the original hard drive to the new hard drive when the D drive in the crashed hard drive is in a normal state (a problem case caused by the OS).

Note: Perform Step 2 after upgrading if the CXDI version you are using is newer than that in the hard drive provided by copying from hard drive to hard drive during system installation.

(Files such as Str.ini are not compatible when the CXDI version is different.)

* When the hard drive has crashed mechanically, proceed to Step 2 and subsequent steps.

- 2) After replacement, copy to overwrite all the ini files stored on the floppy disk to d:\ccr in order to recover the user's environment.

Note that images captured by users cannot be inherited in this case.

Note: Calibration is required when the system has been used for over one year.

Note: Perform Step 2 after upgrade if the CXDI version you are using is newer than that in the hard drive provided by copying from hard drive to hard drive during system installation.

(Files such as Str.ini are not compatible when the CXDI version is different.)

2.4 When problems occur in driver software

When drivers such as the touch panel driver are damaged, reinstall the appropriate drivers by referring to "C3S Service Manual".

6. Troubleshooting

-Reference-

The following describes Windows XP activation for your reference.

(Note that this information is based on a test and information posted on Web bulletin boards because Microsoft does not provide an official document for this.)

1. With or without reactivation required


Modification	1. With or without reactivation required	Description
Reinstalling OS without hard drive formatting required	Not required	
Reinstalling OS with hard drive formatting required	Required	Because an install ID stored in the hard drive is cleared.
Replacing a mother board	Probably required	Depends on the number of on-board devices.
Move a hard drive to a different machine	Required	Due to being regarded as anything other than the hard drive being modified.
Changing external devices	Not required	Due to recognizing the PC's internal configuration only.
Adding hardware components	Not required	Only replacement of components that existed at the time of first activation is detected. Adding components is a different category.

2. Hardware components related to activation

- Display adapter (video board)
- SCSI adapter
- IDE adapter
- Network adapter (MAC address)
- Within the amount of mounted physical memory
- Processor type
- Processor serial number
- Hard disk interface
- Hard disk volume serial number
- CD-ROM/CD-RW/DVD-ROM

3. The number of changed components that require no reactivation

- Without network interface: Changes up to four elements
- With network interface: Changes up to six elements

Error Code List for Version 6.00^⑤

Seriousness (Message Area #1)		Automatic Display	Blinking of “ERR”	Meaning
1	Fatal Error	Yes	Yes	The whole screen blinks in red and the alert window appears automatically. System cannot be recovered. A service person must be called.
2	Alert	Yes	Yes	A red ERR key blinks and alert window appears automatically. Exposure cannot be continued unless the user performs some operation.
3	Error	Yes	No	A red ERR key is displayed and alert window appears automatically. The ERR key does not blink. The possibility of recovering the system by the user is higher than Alert.
4	Warning	No	Yes	An yellow ERR key blinks. Alert window does not appear unless the ERR key is touched.
5	Attention	No	No	An yellow ERR key is displayed. It does not blink. Alert window does not appear unless the ERR key is touched.

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-100 Fatal	OK	#1:Fatal Error #2:Sensor Unit: SelfCheck Error #3:Detected an Error. #4:ER(n) (xxxx) xxxx: Error code [Cause] An undefined error has been found in the sensor A/D board. [Operation after Reply Key is touched] Nothing
-102 Fatal	-14 -15 -95 -98	Error in starting the task in DLL (Failed to begin thread.) Error in DLL resource (Driver does not start.) Number of sensor units is incorrect (No sensor unit is connected.) Capture device cannot be found.
-103 Fatal	Shut Down	#1:Fatal Error #2:READ Timeout Error #3:Failed to transmit the data. [Cause] Image transferring from Ethernet has failed. [Operation after Reply Key is touched] For “Reply” cannot be done, the system must be shutdown.
-105 Fatal	OK	#1:Fatal Error #2:CXDCAP.INI Open Error #3:Install CXDCAP.INI file. [Cause] The cxdcap.ini file has not been installed. [Operation after Reply Key is touched] The system enters a fatal condition. All the sensor units will therefore be disconnected. A service person needs to be called in. However, you can transfer the image and use the study list.
	-97	No cxdcap.ini file is found.

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-522 Fatal	OK	<p>#1:Fatal Error #2:File Open Error:<i>filename</i> #3:File is not found.</p> <p>[Cause] For some reason, XXXX.BIN and XXXX.DCM files do not exist. Or, they cannot be read.</p> <p>[Operation after Reply Key is touched] Shutting down starts. Although this problem can be solved by using the service tool, users must not use the service tool on their own. Take necessary actions in accordance with the service person's instruction.</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-6 Alert	OK	<p>#1:Alert #2:System Info Error #3:A/D board info is updated.</p> <p>[Cause] The A/D board information is different from the former information. This problem occurs when the version of the A/D board has been updated or when the connected units have been changed. If this error occurs when no such changes have been made, it is attributed to another problem. In this case, a service person needs to be called in.</p> <p>[Operation after Reply Key is touched] The A/D board information is renewed.</p>
-8 Alert	OK	<p>#1:Alert #2:System SelfCheck Error #3:Call a service person and let him/her know the error code.</p> <p>[Cause] An error has been found by a self-check.</p> <p>[Operation after Reply Key is touched] Although imaging is possible, image may be degraded. Therefore, a service person needs to be called in.</p>
-116 Alert	OK	<p>#1:Alert #2:Sensor Unit:SelfCheck Error #3:Detected an Error. #4:ER(n) (xxxx) n: Sensor Index (1 to 4) xxxx: Error code</p> <p>[Cause] An undefined error has been found in the sensor A/D board.</p> <p>[Operation after Reply Key is touched] Nothing</p>
-5002 Alert	OK	<p>#1:Alert #2:OPU-CCR RPC Error #3:OPU-CCR RPC Error.</p> <p>[Cause] For some reason, the CCR software has shut down.</p> <p>[Operation after Reply Key is touched]</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
--- Error	OK	#1:Error #2:File Open Error: <i>filename</i> #3:File is not found. [Cause] The file may have been damaged. [Operation after Reply Key is touched]
-1 Error	OK	#1:Error #2:Error #3: [Cause] Undefined error. This error indicates that it is not defined by the CCR manager. The CCR manager controls various tasks. If an error not defined in tasks occurs, error code “-1” is given to the error and thus displayed. This error rarely appears because now most errors are defined. Take necessary actions referring to the system log for the CCR. Local undefined errors output by the OPU can be identified since they are displayed in the messages box of the OS. [Operation after Reply Key is touched] After you confirm it, touch OK.
-2 Error	OK	#1:Error #2:Insufficient tmp disk space. Output the saved data or erase the backed up data. #3: [Cause] The remaining space in the temporary storage directory dttmp has become less than the specified MB. [Operation after Reply Key is touched] Touch OK after you confirm it.
-3 Error	OK	#1:Error #2:Insufficient que disk space. Output the saved data or erase the backed up data. #3: [Cause] The remaining space in the queue storage directory dtque has become less than the specified amount. Usually, this error does not occur because the error “Insufficient tmp disk space” occurs first. [Operation after Reply Key is touched] Touch OK after you confirm it.

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-120 Error	OK	<p>#1:Error #2:Sensor Unit: SelfCheck Error #3:Detected an Error. #4:ER(n) (xxxx) n: Sensor Index (1 to 4) xxxx: Error code</p> <p>[Cause] An undefined error has been found in the sensor A/D board.</p> <p>[Operation after Reply Key is touched] Nothing</p>
-122 Error	OK	<p>#1:Error #2:Sensor Unit:Control Error #3:Detected Control Error. Call a service person.</p> <p>[Cause] An error in the control line has been detected in the sensor A/D board.</p> <p>[Operation after Reply Key is touched] When OK key is touched, the sensor will be disconnected. (Access will not be made, as the system is in an “abnormal” state.) A service person needs to be called in.</p>
	0xeff3, 0xeff4	<p>“Sensor Unit – Power Box(n)(eff3 or eff4)” 0xeff3: There might be problems in the setting of the cable length (Sensor Power Box and X-ray board cable). 0xeff4: There might be problem that Sensor Power cable is broken. n: Sensor Index (1 to 4)</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-123 Error	OK Cancel	<p>#1:Error #2: Sensor Unit: PLD Error #3: Detected PLD Error. Call a service person.</p> <p>[Cause] A PLD error has been found in the sensor A/D board.</p> <p>[Operation after Reply Key is touched] When OK key is touched, the sensor will be disconnected. (Access will not be made, as the system is in an "abnormal" state.) If this error persists even after the system is rebooted, a service person needs to be called in.</p>
	0xeff8 0xeff7	<p>"PLD err (n)(eff8)" "PLD Config err (n)(eff7)"</p> <p>n: Sensor Index (1 to 4)</p>
-125 Error	OK	<p>#1:Error #2:Sensor Unit:Grid Error #3:Because of the Grid error, this image may have a quality problem.</p> <p>[Cause] Although a warning for grid had been detected in the sensor A/D board, imaging was continued. Thus, the image may have been degraded.</p> <p>[Operation after Reply Key is touched] When OK key is touched, the screen returns to the normal display without doing anything.</p>
	0xeffb	<p>"Grid was changed during exposure (n)(effb)"</p> <p>n: Sensor Index (1 to 4)</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-126 Error	OK	<p>#1:Error #2:Sensor Unit:Temperature Error #3:The internal temperature of the Sensor Unit exceeded the temperature limit. Cannot capture images until the temperature goes below the limit. #4:TEMP OVER (n)(effa) n: Sensor Index (1 to 4)</p> <p>[Cause] The sensor temperature has exceeded 45°C. Thus, the error for aborting the operation has been detected. The system cannot be used until the temperature lowers, which will take several tens of minutes.</p> <p>[Operation after Reply Key is touched] The sensors automatically enter the sleep mode. The host computer does nothing. If you try to make the system ready, the same error occurs again. Press the [OK] to close the window, after few minutes later operate again. Note: The error might be able to be evaded by reducing an environmental temperature.</p>
-129 Error	OK	<p>#1:Error #2:Sensor Unit: Data Transmit Error #3:Failed to transmit the data.</p> <p>[Cause] Internal DMA has passed time limit during read the reduced image. Full image data transferring has been interrupted. [Operation after Reply Key is touched] Without anything to do. (Same as usual operation)</p>
	0xEFF0 0xEFEF	
-143 Error	OK	<p>#1:Error #2:Calibration Table Error #3:Perform Calibration.</p> <p>[Cause] No gain calibration table has been prepared. Or, the serial number of the connected sensor unit is different.</p> <p>[Operation after Reply Key is touched] Perform calibration to make a gain calibration table.</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-144 Error	OK	<p>#1:Error #2:Sensor Unit Configuration #3:Incorrect Senor Unit Configuration. Call a service person. #4:Invalid Serial No.(n)(eff5 or eff6)</p> <p>n: Sensor Index (1 to 4)</p> <p>[Cause] 0xeff5: Caused by that the differences has been in serial number and DP number. 0xeff6: Caused by that false serial number has written.</p> <p>[Operation after Reply Key is touched] When OK button is touched, sensor is disconnected. A service person needs to be called in. (Keep unusual state, and do not access.)</p>
-302 Error	OK	<p>#1:Error #2:Calibration Error #3:Too Much Dose. Or collimator is used.</p> <p>[Cause] Excessive dose of radiation was used in exposure of image for white correction.</p> <p>[Operation after Reply Key is touched] Perform imaging again.</p>
-303 Error	OK	<p>#1:Error #2:Calibration Error #3:Too Little Dose. Or collimator is used.</p> <p>[Cause] Insufficient dose of radiation was used in exposure of image for white correction.</p> <p>[Operation after Reply Key is touched] Perform imaging again.</p>
-304 Error	OK	<p>#1:Error #2:Calibration Error #3:Invalid Data. Or collimator is used.</p> <p>[Cause] Too much difference in dose acquired by the panels.</p> <p>[Operation after Reply Key is touched] Perform imaging again.</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-305 Error	OK	#1:Error #2:Calibration Error #3:Collimator may be used. [Cause] This error is not currently used. [Operation after Reply Key is touched] Perform imaging again.
-306 Error	OK	#1:Error #2:QA Process Error #3:Image Analysis Error. Adjust image process parameter manually. [Cause] Feature extraction may have failed. [Operation after Reply Key is touched] The user must process the image manually.
-310 Error	OK	#1:Error #2:REX Value Warning #2:REX Value Warning #3:REX is 999. It is under the minimum limitation value 9999. Please reconfirm the generator setting or exposure condition. If the condition is correct, adjust the image processing. [Cause] This error occurs when the REX value acquired by image processing after the imaging is less than the limitation value. [Operation after Reply Key is touched] Nothing [Note] 999: REX value obtained by image processing 9999: lower limit value

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-311 Error	OK	<p>#1:Error #2:REX Value Warning #3:REX is 9999. It is under the maximum limitation value 999. Please reconfirm the generator setting or exposure condition. If the condition is correct, adjust the image processing.</p> <p>[Cause] This error occurs when the REX value acquired by image processing after the imaging is more than the limitation value.</p> <p>[Operation after Reply Key is touched] Nothing</p> <p>[Note] 9999: REX value obtained by image processing 999: upper limit value</p>
-402 Error	OK	<p>#1:Error #2:Incomplete End Error #3:The last image in the last study was not saved completely.</p> <p>[Cause] Failed to write in the last image of the previous imaging.</p> <p>[Operation after Reply Key is touched] If there remain the previous images, they will be recovered.</p>
-403 Error	OK	<p>#1:Error #2:Incomplete End Error #3:Do you want store captured images into internal storage in order to recover them later? (Name of the patient) (Number of images)</p> <p>[Cause] The last image(s) was not queued due to incomplete end in the previous imaging.</p> <p>[Operation after Reply Key is touched] When Ok is chosen, the recovery process will start. When Cancel is chosen, the last images will be deleted. In this case, normal exposure for imaging will start without recovering the last images. When CANCEL is chosen, a confirmation message will appear before deleting the image.</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-509 Error	OK	<p>#1:Error #2:External Storage Error: #3:Selected directory or disk for storage can only be read.</p> <p>[Cause] The external storage medium for the stored data is read-only.</p> <p>[Operation after Reply Key is touched] The system returns to the state before the occurrence of the error.</p>
-512 Error	OK	<p>#1:Error #2:External Storage Error: #3:Cannot recognize the removable disk. Set the disk properly and retry.</p> <p>[Cause] No medium is found in the removable disk.</p> <p>[Operation after Reply Key is touched] The system returns to the state before the occurrence of the error.</p>
-513 Error	OK	<p>#1:Error #2:Media Control Error #3:Operation has been canceled because the external storage or directory is busy.</p> <p>[Cause] The external medium is busy deleting or writing the data. This error occurs such as when you try to eject the disk while the external medium is busy.</p> <p>[Operation after Reply Key is touched] After you confirm it, touch OK.</p>
-514 Error	OK	<p>#1:Error #2:External Storage Error: #3:The exposed images cannot be stored because the size of folder partition is smaller than the exposed images. Use a new disk, erase the folder contents or enlarge the folder size and retry.</p> <p>[Cause] An image cannot be stored into a folder in the external storage medium when the size of the folder is smaller than the image. Enlarge the folder size in the system setting.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, the image is stored again, while selecting CANCEL cancels storing the image to the external storage medium. When CANCEL is chosen, a confirmation message appears before deleting the image.</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-517 Error	OK	<p>#1:Error #2:Internal Storage Error: #3:Processed image cannot be stored, because the capacity of internal storage memory is insufficient.</p> <p>[Cause] The remaining space in the internal disk is insufficient.</p> <p>[Operation after Reply Key is touched] The system returns to the state before the occurrence of the error.</p>
-518 Error	OK	<p>#1:Error #2:Internal Storage Error: #3:DICOM image cannot be stored, because the capacity of internal storage memory is insufficient.</p> <p>[Cause] There is not enough space for storing DICOM image.</p> <p>[Operation after Reply Key is touched] The system returns to the state before the occurrence of the error.</p>
-519 Error	OK	<p>#1:Error #2:External Storage Error: #3:Capacity of external storage memory is insufficient. Retry after making a space in the disk.</p> <p>[Cause] The space in the external storage medium is insufficient.</p> <p>[Operation after Reply Key is touched] The system returns to the state before the occurrence of the error.</p>
-520 Error	OK	<p>#1:Error #2:Internal Storage Error: #3:Exposed image cannot be stored, because the capacity of internal storage memory is insufficient.</p> <p>[Cause] The remaining space in the internal disk is insufficient.</p> <p>[Operation after Reply Key is touched] The system returns to the state before the occurrence of the error.</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-521 Error	OK	<p>#1:Error #2:Queue File Open Error: #3:Queue file is not found.</p> <p>[Cause] Failed to open the queue file. This error occurs when no queue file exists.</p> <p>[Operation after Reply Key is touched] *Under the current system, this error is unlikely to occur.</p>
-599 Error	OK	<p>#1:Error #2:File Open Error: #3:File is not found.</p> <p>[Cause] This error occurs when the system has failed to open the file during RESEND.</p> <p>[Operation after Reply Key is touched] Just touch OK. The system returns to the state before the occurrence of the error.</p>
-601 Error	OK	<p>#1:Error #2:Resend Error #3:File may have been automatically deleted.</p> <p>[Cause] The image cannot be resend as it was deleted for some reason while being called out.</p> <p>[Operation after Reply Key is touched] The image being displayed on the re-print screen is made invalid and the image can no longer be resend.</p>
-5100 Error	OK	<p>#1:Error #2:Sensor Unit:Detect Error #3:Check the sensor power unit or cable connection. If you want to recover the system, shut it down.</p> <p>[Cause] The power of the imaging unit is OFF, or the cable is disconnected or damaged.</p> <p>[Operation after Reply Key is touched] The system only requires your confirmation. Touch OK. Only the problematic sensor is disabled.</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-5101 Error	OK	<p>#1:Error #2:Sensor Unit:Detect Error #3:Check the sensor unit cable connection. If you want to recover the system, shut it down.</p> <p>[Cause] The cable is not connected though it is setting which uses the sensor.</p> <p>[Operation after Reply Key is touched] The system only requires your confirmation. Touch OK. Only the problematic sensor is disabled.</p>
-5102 Error	OK	<p>#1:Error #2:Grid Error #3:Remove Grid for this exposure.</p> <p>[Cause] This error occurs when grids are detected in the Buck/Cassette setting, where imaging is expected to be performed without grids.</p> <p>[Operation after Reply Key is touched] Touch OK after the check.</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-150 Warning	OK	<p>#1:Warning #2:Sensor Unit:SelfCheck Error #3:Detected an Error. #4:ER(n) (xxxx) #4:"Firm PLD err(n) (eff1 or eff2) 0xeff1: Failure has been detected in the received Hex format file during the Firm/PLD/DP files are downloading. 0xeff2: Failure has been detected in the received Hex format file during the Firm/PLD are downloading.</p> <p>n: Sensor Index (1 to 4) xxxx: Error code</p> <p>[Cause] An undefined error has been found in the sensor A/D board.</p> <p>[Operation after Reply Key is touched] Nothing.</p>
-151 Warning	OK	<p>#1:Warning #2:Sensor Unit:Flash ROM Error #3:Detected Flash ROM Error. Call a service person.</p> <p>[Cause] A warning on the flash ROM has been detected in the sensor A/D board.</p> <p>[Operation after Reply Key is touched] When OK key is touched, the screen returns to the normal display. Imaging can be performed by touching the exposure mode key again. Although imaging can be performed, a service person needs to be called in.</p>
	0xeffe 0xeffd 0xeffc	<p>"F-ROM ID err (n)(effe)" "F-ROM write err (n)(effd)" "F-ROM erase err (n)(effc)"</p> <p>n: Sensor Index (1 to 4)</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-153 Warning	OK	<p>#1:Warning #2:Sensor Unit:Temperature Warning #3:The internal temperature of the Sensor Unit approaches the temperature limit. Do not leave in the READY condition of the Sensor Unit.. #4:TEMP OVER (n)(eff9) n: Sensor Index (1 to 4)</p> <p>[Cause] The warning sign is detected because the internal temperature of Imaging unit has approached the upper bound value.</p> <p>[Operation after Reply Key is touched] The sensor selfishly enters the state of sleep. There is nothing to operate at the host side. The same error occurs when the user tries to put this sensor into the state of READY. In this case, press the [OK] to close the window and continue to operate. This error might be able to be evated by reducing the internal temperature or having the Imaging unit READY STATE TIME shorten.</p>
-502 Warning	RETRY CANCEL	<p>#1:Warning #2:DICOM Connect Error #3:Cannot connect to target. Check network or port number setting.</p> <p>[Cause] Cannot be connected to the destination.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, the image will be transferred again. When CANCEL is chosen, transfer will be canceled after displaying a confirmation message. Re-transfer is possible by sending the image from the study list.</p>
-503 Warning	RETRY CANCEL	<p>#1:Warning #2:DICOM Transfer Error #3>Error has occurred during association.</p> <p>[Cause] Network was cut off during the communication.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, the image will be transferred again. When CANCEL is chosen, transfer will be cancelled after displaying a confirmation message. Re-transfer is possible by transferring the image from the study list.[990914]</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-504 Warning	RETRY CANCEL	<p>#1:Warning #2:DICOM Parameter Error #3:DICOM transfer Parameter is wrong.</p> <p>[Cause] DICOM transfer parameters are not correct.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, the image will be transferred again. When CANCEL is chosen, transfer will be canceled after displaying a confirmation message. Enter the correct parameters and transfer the image from the study list again.</p>
-505 Warning	RETRY CANCEL	<p>#1:Warning #2:DICOM Response Error #3:Receiving device reported an error in DICOM response. Check receiving device.</p> <p>[Cause] DICOM response was received properly. However, the target reported an error as a response.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, the image will be transferred again. When CANCEL is chosen, transfer will be canceled after displaying a confirmation message. Re-transfer is possible by sending an image from the study list.</p>
-507 Warning	RETRY CANCEL	<p>#1:Warning #2:DICOM Printer Status Error #3:CXDI has aborted DICOM transmission because of a FAILURE in DICOM printer status. Check receiving device.</p> <p>[Cause] DICOM printer status was received properly. However, the target reported a FAILURE as printer status, and so the image transfer was cancelled.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, the image will be transferred again. When CANCEL is chosen, the transfer will be cancelled after displaying a confirmation message. Re-transfer is possible by sending the image from the study list.</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-509 Warning	RETRY CANCEL	<p>#1:Warning #2:External Storage Error: #3:Selected directory or disk for storage can only be read.</p> <p>[Cause] The external storage medium is read-only.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, the image will be stored. When CANCEL is chosen, the storage of image to external storage medium will be cancelled after displaying a confirmation message. Re-transfer is possible by sending the image from the study list again.</p>
-510 Warning	RETRY CANCEL	<p>#1:Warning #2:External Storage Error: #3:Selected directory or disk for storage does not exist. Or image cannot be saved on external storage, because the external storage or directory is not properly set.</p> <p>[Cause] There is no directory or disk in the destination. Or, recording cannot be performed due to system function error.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, the image will be stored again. When CANCEL is chosen, storing the image into external storage medium will be cancelled after displaying a confirmation message. Re-transfer is possible by sending the image from the study list again.</p>
-512 Warning	RETRY CANCEL	<p>#1:Warning #2:External Storage Error: #3: Cannot recognize the removal disk. Set the disk properly and retry.</p> <p>[Cause] Disk is not inserted.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, the image will be stored. When CANCEL is chosen, storing of image will be cancelled after displaying a confirmation message. Re-transfer is possible by sending the image from the study list.</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-514 Warning	RETRY CANCEL	<p>#1:Warning #2:External Storage Error: #3:The exposed images cannot be stored because the size of folder partition is smaller than the exposed images. Use a new disk, erase the folder contents or enlarge the folder size and retry. (The size of folder partition: xxxxMB) (The size of exposed images: xxxxMB)</p> <p>[Cause] Images cannot be stored into the folder when the folder size of the external storage medium is smaller than a study.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, the image will be stored. When CANCEL is chosen, storing of image will be cancelled after displaying a confirmation message. Re-transfer is possible by transferring the image from the study list.</p>
-515 Warning	RETRY CANCEL	<p>#1:Warning #2:Internal Storage Error: #3:Selected directory for storage can only be read.</p> <p>[Cause] The external storage medium is read-only. Use a writable external storage medium.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, the image will be stored into the internal disk. When CANCEL is chosen, storing of image will be cancelled after displaying a confirmation message. Re-transfer is possible by sending the image from the study list.</p>
-516 Warning	RETRY CANCEL	<p>#1:Warning #2:Internal Storage Error: #3:Selected directory for storage does not exist, or attribution is incorrect.</p> <p>[Cause] There is no directory in the destination, or recording cannot be performed due to system function error.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, the image will be stored into the internal disk. When CANCEL is chosen, storing of image will be cancelled after displaying a confirmation message. Retransfer is possible by sending the image from the study list.</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-517 Warning	RETRY	<p>#1:Warning #2:Internal Storage Error: #3:Processed image cannot be stored, because the capacity of internal storage memory is insufficient.</p> <p>[Cause] The space in the internal disk is insufficient.</p> <p>[Operation after Reply Key is touched] QA process will be performed again.</p>
-518 Warning	RETRY CANCEL	<p>#1:Warning #2:Internal Storage Error: #3:DICOM image cannot be stored, because the capacity of internal storage memory is insufficient.</p> <p>[Cause] There is not enough space for storing DICOM image.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, image will be stored into the internal disk. When CANCEL is chosen, storing of image will be cancelled after displaying a confirmation message.</p>
-519 Warning	RETRY CANCEL	<p>#1:Warning #2:External Storage Error: #3:Capacity of external storage memory is insufficient. Retry after making a space in the disk.</p> <p>[Cause] There is not enough space in the external storage medium.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, image will be stored into the external storage medium. When CANCEL is chosen, storing of image will be cancelled after displaying a confirmation message.</p>
-520 Warning	OK	<p>#1:Warning #2:Internal Storage Error: #3:Exposed image cannot be stored, because the capacity of internal storage memory is insufficient.</p> <p>[Cause] Space in the internal disk is insufficient.</p> <p>[Operation after Reply Key is touched] When RETRY is chosen, the image will be stored into the internal disk. When CANCEL is chosen, storing of image will be cancelled after displaying a confirmation message.</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-6000 Warning	OK	<p>#1:Warning #2:Calibration Error #3:<i>STAND</i>(SENSOR-ID:XXX) <i>Time</i> have passed since the last calibration Calibrate now.</p> <p>[Cause] This error occurs when calibration has not been performed within the set time.</p> <p>[Operation after Reply Key is touched] The calibration screen appears to prompt you to perform calibration.</p>

Error Code Seriousness	Reply Keys	Message [Cause] [Operation after Reply Key is touched]
-506 Attention	OK	<p>#1:Attention #2:DICOM Response Warning #3:Although transfer finished properly, receiving device reported a warning in DICOM response. Check receiving device.</p> <p>[Cause] DICOM response was received properly. However, the target reported a warning as a response.</p> <p>[Operation after Reply Key is touched] Checks only if the system is OK because the system is normal.</p>
-508 Attention	OK	<p>#1:Attention #2:DICOM Printer Status Warning #3:Although transfer finished normally, receiving device reported an WARNING in DICOM printer status. Check receiving device.</p> <p>[Cause] DICOM printer status was received properly. However, the target reported a WARNING as printer status.</p> <p>[Operation after Reply Key is touched] Only checks if the system is OK.</p>
-511 Attention	OK	<p>#1:Attention #2:External Storage Attention: #3:Remaining space in external storage is less than XXX %.</p> <p>[Cause] (Space x 100)/Total capacity of the external storage medium has exceeded the XXX % set in dtDsRestPercent.</p> <p>[Operation after Reply Key is touched] Only checks if the system is OK.</p>

CXDI-50G

7. Service Manual Report