

MODIFICATION INSTRUCTIONS

for the

KODAK MULTILOADER 700

Service Code 3053

Modification No. 17

TYPE 2

PURPOSE:

To improve the function of the SWITCHES S1, S2 and S3.

SERIAL NUMBERS: for 50Hz Units up to SN 1937

for 60Hz Units up to SN 5835

INSTALLATION TIME: Approx. 0.5 hours

PARTS REQUIREMENTS: Modification Kit 9193205

PLEASE NOTE

The information contained herein is based on the experience and knowledge relating to the subject matter gained by Kodak prior to publication.

No patent license is granted by this information.

Kodak reserves the right to change this information without notice, and makes no warranty, express or implied, with respect to this information. Kodak shall not be liable for any loss or damage, including consequential or special damages, resulting from the use of this information, even if loss or damage is caused by Kodak's negligence or other fault.

PARTS LIST

<u>PART-NO.</u>	<u>DESCRIPTION</u>	<u>QUANTITY</u>
9193205.....	MOD KIT 17	

The KIT contains:

4480391	WASHER.....	1
9193291	LEAF-SPRING.....	1
9193321	ACTUATOR.....	1
4281661	SCREW	2

INTRODUCTION

To prevent the ACTUATOR WIRES from the SWITCHES S1, S2 and S3 staying in the upper position, the LEAF-SPRING is installed.

INSTALLATION

1. Switch off the ML700.
2. Open the TOP COVER of the ML700 and secure it.
3. Mount the ACTUATOR and the LEAF-SPRING to the SHAFT.




figure 1

4. Adjust the position of the ACTUATOR, that the LEAF-SPRING presses with little force onto the 3 WIRE ACTUATORS of S1, S2 and S3. Only a little force is needed to prevent the WIRE ACTUATORS from staying in the upper position. If the force is too high, it may result in CASSETTE TRANSPORT PROBLEMS.
5. Tighten the 2 SCREWS of the ACTUATOR.

6. Circle No. 17 on the MODIFICATION LABEL of the ML700.




figure 2

FINAL TEST

1. Override the TOP COVER INTERLOCK.
2. Switch on the ML700.
3. Select the UNLOAD MODE of the ML700 to prevent the MAGAZINES from opening and unload a CASSETTE through the ML700 and check for correct operation of S1, S2 and S3.
4. Take out the override from the TOP COVER INTERLOCK and close the TOP COVER.
5. Run a few more cycles and check for correct operation.



CUSTOMER EQUIPMENT SERVICES KODAK AG STUTTGART GERMANY



CUSTOMER EQUIPMENT SERVICES KODAK AG STUTTGART GERMANY